IEC 60034-26

Edition 2.0 2026-01

INTERNATIONAL STANDARD

REDLINE VERSION

Rotating electrical machines -
Part 26: Effects of unbalanced voltages on the performance of three-phase cage induction motors

ICS 29.160.01

ISBN 978-2-8327-1009-8

CONTENTS

FOREWORD 2
INTRODUCTION 4
1 Scope 5
2 Normative references 5
3 Terms and definitions 5
4 Effects of unbalanced voltages on performance 5
4.1 General 5
4.2 Currents 5
4.3 Heating 5
4.4 Torque 5
4.5 Full-load speed 6
4.6 Efficiency 6
5 Derating of motor to prevent overheating 6
~~Annex A (informative) Worked example~~ .....
Annex A (informative) Determination of the symmetrical components of the line-to-line voltages U1, U2, U3 of a three-phase system 10
A.1 Graphical determination 10
A.2 Analytical determination 11
Annex B (informative) Approximate determination of the unbalance factor 12
Bibliography 13

Figure 1 – Typical values of derating of design N or NE, three-phase cage induction motors within the scope of IEC 60034-12 8
Figure A.1 – Phasor diagram 10

INTERNATIONAL ELECTROTECHNICAL COMMISSION

_____

Rotating electrical machines - Part 26: Effects of unbalanced voltages on the performance of three-phase cage induction motors

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at https://patents.iec.ch. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition IEC 60034-26:2006. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

IEC 60034-26 has been prepared by IEC technical committee 2: Rotating machinery. It is an International Standard.

This second edition cancels and replaces the first edition published in 2006. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

a) clarification that voltages are line-to-line voltages in Clause 4, Annex A and Annex B;

b) addition of design NE according to IEC 60034-12 in Clause 4.

The text of this International Standard is based on the following documents:

Draft	Report on voting
2/2224/CDV	2/2251/RVC

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

A list of all parts of IEC 60034 series, under the general title *Rotating electrical machines* can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

– reconfirmed,

– withdrawn, or

– revised.

INTRODUCTION

When the line voltages applied to a three-phase cage induction motor are not ~~equal~~ a balanced, symmetric three-phase system, the currents in the phases of the stator winding will also be unequal. A small percentage voltage unbalance will result in a much larger percentage current unbalance.

The application of unbalanced voltages to a three-phase induction motor introduces a negative sequence voltage, and this produces a flux in the air-gap~~, a flux~~ rotating against the rotation of the rotor, thus ~~tending to produce high currents~~ having a slip of almost 200 %. For high values of the slip, the motor impedance is low, thus tending to produce a high negative sequence current in the stator winding and high currents in the rotor cage. A small negative sequence voltage ~~may~~ can produce currents in the ~~windings~~ winding phases considerably in excess of those present under balanced voltage conditions. Consequently, the temperature rise of the motor operating at a particular load and a particular percentage of voltage unbalance will be ~~greater~~ higher than for the motor operating under the same conditions with balanced voltages.

The analytical and graphical methods used to calculate the symmetrical components from the voltage readings of the three phases are well-known and can be taken from textbooks. Thus, these calculation schemes are not incorporated in this document but shown in the informative Annex A. Besides, the evaluation of the symmetrical components can be done automatically by modern instrumentation.

An approximate evaluation of imbalance is given in the informative Annex B.

1 Scope

This part of IEC 60034 describes the effects of unbalanced voltages on the performance of three-phase cage induction motors.

2 Normative references

~~The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.~~

~~IEC 60034-12, *Rotating electrical machines – Part 12: Starting performance of single-speed three-phase cage induction motors*~~

There are no normative references in this document.

Bibliography

IEC 60034-12:2024, *Rotating electrical machines - Part 12: Starting performance of single-speed three-phase cage induction motors*

_____