IEC 61558-2-12

Edition 3.0 2024-04
REDLINE VERSION

INTERNATIONAL STANDARD

colour inside

GROUP ENERGY EFFICIENCY PUBLICATION

Safety of transformers, reactors, power supply units and combination thereof – Part 2-12: Particular requirements and tests for constant voltage transformers and power supply units for constant voltage

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 29.180

ISBN 978-2-8322-8741-5

Warning! Make sure that you obtained this publication from an authorized distributor.

® Registered trademark of the International Electrotechnical Commission

CONTENTS

FOREWORD 3
INTRODUCTION 2
1 Scope 7
2 Normative references 9
3 Terms and definitions 9
4 General requirements 9
5 General notes on tests 10
6 Ratings 10
7 Classification 11
8 Marking and other information 11
9 Protection against electric shock 11
10 Change of input voltage setting 13
11 Output voltage and output current under load 13
12 No-load output voltage 14
13 Short-circuit voltage 15
14 Heating 15
15 Short-circuit and overload protection 15
16 Mechanical strength 16
17 Protection against harmful ingress of dust, solid objects and moisture 17
18 Insulation resistance, dielectric strength and leakage current 17
19 Construction 18
20 Components 18
21 Internal wiring 22
22 Supply connection and other external flexible cables or cords 22
23 Terminals for external conductors 22
24 Provisions for protective earthing 22
25 Screws and connections 22
26 Creepage distances, clearances and distances through insulation 23
27 Resistance to heat, fire and tracking 23
28 Resistance to rusting 23
Annexes 24
~~Annex C (normative) .....~~
~~Annex D (normative) .....~~
Annex L (normative) Routine tests (production test) 24
~~Annex R (normative) .....~~
Bibliography 25

Table 101 – Symbols indicating the kind of transformer 12

INTERNATIONAL ELECTROTECHNICAL COMMISSION

_____

SAFETY OF TRANSFORMERS, REACTORS, POWER SUPPLY UNITS AND COMBINATIONS THEREOF –

Part 2-12: Particular requirements and tests for constant voltage transformers and power supply units for constant voltage

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at https://patents.iec.ch. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition IEC 61558-2-12:2011. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

IEC 61558-2-12 has been prepared by IEC technical committee 96: Transformers, reactors, power supply units and combinations thereof. It is an International Standard.

This third edition cancels and replaces the second edition published in 2011. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

a) adjustment of structure and references in accordance with IEC 61558-1:2017;
b) description of constructions moved to IEC 61558-1:2017;
c) new symbol for power supply unit with linearly regulated output voltage.

The text of this International Standard is based on the following documents:

Draft	Report on voting
96/587/FDIS	96/591/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

It has the status of a group safety publication in accordance with IEC Guide 104.

This International Standard is to be used in conjunction with IEC 61558-1:2017.

This document supplements or modifies the corresponding clauses in IEC 61558-1:2017, so as to convert that publication into the IEC standard: *Particular requirements and tests for constant voltage transformers and power supply units for constant voltage.*

A list of all parts in the IEC 61558 series published under the general title *Safety of transformers, reactors, power supply units and combinations thereof,* can be found on the IEC website.

Future standards in this series will carry the new general title as cited above. Titles of existing standards in this series will be updated at the time of the next edition.

Where this document states "*addition*", "*modification*" or "*replacement*", the relevant text of IEC 61558-1:2017 is to be adopted accordingly.

In this document, the following print types are used:

– requirements proper: in roman type;
– *test specifications: in italic type*;
– explanatory matter: in smaller roman type:

In the text of this document, the words in **bold** are defined in Clause 3.

Subclauses, notes, figures and tables additional to those in IEC 61558-1:2017 are numbered starting from 101; supplementary annexes are entitled AA, BB, etc.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

IEC TC 96 has a group safety function in accordance with IEC Guide 104 for transformers other than those intended to supply distribution networks, in particular transformers and power supply units intended to allow the application of protective measures against electric shock as defined by TC 64, which is about electrical installations and protection against electric shock, but in certain cases including the limitation of voltage and horizontal safety function for SELV, in accordance with IEC 60364-4-41.

The group safety function (GSF) is used because of responsibility for safety extra-low voltage (SELV) in accordance with IEC 61140:2016, 5.2.6 and IEC 60364-4-41:2005, 414.3.1 or control circuits in accordance with IEC 60204-1:2016, 7.2.4.

The group safety function is used for each part of IEC 61558-2 because different standards of the IEC 61558 series can be combined in one construction but in certain cases with no limitation of rated output power.

For example an auto-transformer in accordance with IEC 61558-2-13 can be designed with a separate SELV-circuit in accordance with the particular requirements for IEC 61558-2-6 relating to the general requirements of IEC 61558-1.

SAFETY OF TRANSFORMERS, REACTORS, POWER SUPPLY UNITS AND COMBINATIONS THEREOF –

Part 2-12: Particular requirements and tests for constant voltage transformers and power supply units for constant voltage

1 Scope

Replacement:

This part of IEC 61558 deals with the safety of **constant voltage transformers** for general applications and **power supply units for constant voltage** for general applications. **Constant voltage transformers** incorporating **electronic circuits** are also covered by this document.

NOTE 1 Safety includes electrical, thermal and mechanical aspects.

Unless otherwise specified, from here onward, the term **transformer** covers **constant voltage transformers** for general applications and **power supply units for constant voltage** for general applications.

This document is applicable to **stationary** or **portable** single-phase or polyphase, air-cooled (natural or forced) **independent** or **associated dry-type**:

– **constant voltage auto-transformers**;
– **constant voltage separating transformers**;
– **constant voltage isolating transformers**;
– **constant voltage safety isolating transformers**.

The windings ~~may~~ can be encapsulated or non-encapsulated.

~~This standard is applicable to **transformers** and **power supply** (linear) with internal operating frequencies not exceeding 500 Hz.~~

~~This standard used in combination with Part 2-16 for **switch mode power supply** (SMPS) units is also applicable to power supplies with internal operating frequencies higher than 500 Hz. Where the two requirements are in conflict, the most severe take precedence.~~

For **power supply units** (linear) this document is applicable. For **switch mode power supply units** IEC 61558-2-16 is applicable together with this document. Where two requirements are in conflict, the most severe take precedence.

The **rated supply voltage** does not exceed 1 000 V AC. The **rated supply frequency** does not exceed 500 Hz, the **internal operating resonant frequency** does not exceed 30 kHz and the **internal operating frequency** does not exceed 100 MHz.

The **rated output** does not exceed:

– 40 kVA for single-phase **constant voltage auto-transformers**;
– 200 kVA for polyphase **constant voltage auto-transformers**;
– 25 kVA for single-phase **constant voltage separating transformers** and **constant voltage isolating transformers**;

– 40 kVA for polyphase **constant voltage separating transformers** and **constant voltage isolating transformers**;

– 10 kVA for single-phase **constant voltage safety isolating transformers**;

– 16 kVA for polyphase **constant voltage safety isolating transformers.**

This document is applicable to **transformers** without limitation of the **rated output**, subject to an agreement between the purchaser and the manufacturer.

NOTE 2 **Transformers** intended to supply distribution networks are not included in the scope.

Where applicable to **constant voltage auto-transformers**

– the **no-load output voltage** or the **rated output voltage** does not exceed 1 000 V AC or 1 415 V ripple-free DC, and for **independent constant voltage auto-transformers** the **no-load output voltage** and the **rated output voltage** exceed 50 V AC or 120 V ripple-free DC;

– **constant voltage auto-transformers** covered by this document are used only in applications where no **insulation** between circuits is required by the installation rules or by the end product standard.

Where applicable to **constant voltage separating transformers**

– the **no-load output voltage** or the **rated output voltage** does not exceed 1 000 V AC or 1 415 V ripple-free DC, and for **independent constant voltage separating transformers** the **no-load output voltage** and the **rated output voltage** exceed 50 V AC or 120 V ripple-free DC;

– **constant voltage separating transformers** covered by this document are used only in applications where **double** or **reinforced insulation** between circuits is not required by the installation rules or by the end product standard.

Where applicable to **constant voltage isolating transformers**

– the **no-load output voltage** or the **rated output voltage** does exceed 50 V AC or 120 V ripple-free DC and where applicable, does not exceed 500 V AC or 708 V ripple-free DC. The **no-load output voltage** and the **rated output voltage** ~~may~~ can be up to 1 000 V AC or 1 415 V ripple-free DC for special applications;

– **constant voltage isolating transformers** covered by this document are used only in applications where **double** or **reinforced insulation** between circuits is required by the installation rules or by the end product standard.

Where applicable to **constant voltage safety isolating transformers**

– the **no-load output voltage** or the **rated output voltage** does not exceed 50 V AC or 120 V ripple-free DC;

– **constant voltage safety isolating transformers** covered by this document are used only in applications where **double** or **reinforced insulation** between circuits is required by the installation rules or by the end product standard.

This document is not applicable to external circuits and their components intended to be connected to the input terminals and output terminals of the **transformers**.

~~NOTE 3~~ Attention is drawn to the following if necessary:

– for **transformers** intended to be used in vehicles, on board ships, and aircraft, additional requirements (from other applicable standards, national rules, etc.) ~~may be necessary~~;

– measures to protect the **enclosure** and the components inside the enclosure against external influences such as fungus, vermin, termites, solar-radiation, and icing ~~should also be considered~~;

– the different conditions for transportation, storage, and operation of the **transformers** ~~should also be considered~~;

– additional requirements in accordance with other appropriate standards and national rules may be applicable to **transformers** intended for use in special environments.

~~NOTE 4~~ Future technological development of **transformers** may necessitate a need to increase the upper limit of the frequencies. Until then this document may be used as a guidance document.

This group safety publication focusing on safety guidance is primarily intended to be used as a product safety standard for the products mentioned in the scope, but is also intended to be used by technical committees in the preparation of publications for products similar to those mentioned in the scope of this group safety publication, in accordance with the principles laid down in IEC Guide 104 and ISO/IEC Guide 51.

One of the responsibilities of a technical committee is, wherever applicable, to make use of basic safety publications and/or group safety publications in the preparation of its publications.

2 Normative references

This clause of IEC 61558-1:2017 is applicable except as follows:

Addition

IEC 61558-1:2017, *Safety of transformers, reactors, power supply units and combinations thereof – Part 1: General requirements and tests*

IEC 61558-2-16:2021, *Safety of transformers, reactors, power supply units and combinations thereof – Part 16: Particular requirements and tests for switch mode power supply units and transformers for switch mode power supply units for general applications*

IEC 61558-2-12

Edition 3.0 2024-04

INTERNATIONAL STANDARD

NORME INTERNATIONALE

GROUP ENERGY EFFICIENCY PUBLICATION
PUBLICATION GROUPÉE SUR L'EFFICACITÉ ÉNERGÉTIQUE

Safety of transformers, reactors, power supply units and combination thereof – Part 2-12: Particular requirements and tests for constant voltage transformers and power supply units for constant voltage

Sécurité des transformateurs, bobines d'inductance, blocs d'alimentation et des combinaisons de ces éléments – Partie 2-12: Exigences particulières et essais pour les transformateurs à tension constante et les blocs d'alimentation pour tension constante



IEC 61558-2-12:2024-04(en-fr)

CONTENTS

FOREWORD 3
INTRODUCTION 5
1 Scope 6
2 Normative references 8
3 Terms and definitions 8
4 General requirements 9
5 General notes on tests 9
6 Ratings 9
7 Classification 10
8 Marking and other information 10
9 Protection against electric shock 12
10 Change of input voltage setting 12
11 Output voltage and output current under load 12
12 No-load output voltage 13
13 Short-circuit voltage 14
14 Heating 14
15 Short-circuit and overload protection 14
16 Mechanical strength 15
17 Protection against harmful ingress of dust, solid objects and moisture 15
18 Insulation resistance, dielectric strength and leakage current 16
19 Construction 16
20 Components 17
21 Internal wiring 17
22 Supply connection and other external flexible cables or cords 17
23 Terminals for external conductors 17
24 Provisions for protective earthing 17
25 Screws and connections 17
26 Creepage distances, clearances and distances through insulation 17
27 Resistance to heat, fire and tracking 17
28 Resistance to rusting 18
Annexes 19
Annex L (normative) Routine tests (production test) 19
Bibliography 20

Table 101 – Symbols indicating the kind of transformer 11

INTERNATIONAL ELECTROTECHNICAL COMMISSION

_____

SAFETY OF TRANSFORMERS, REACTORS, POWER SUPPLY UNITS AND COMBINATIONS THEREOF –

Part 2-12: Particular requirements and tests for constant voltage transformers and power supply units for constant voltage

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at https://patents.iec.ch. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 61558-2-12 has been prepared by IEC technical committee 96: Transformers, reactors, power supply units and combinations thereof. It is an International Standard.

This third edition cancels and replaces the second edition published in 2011. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

a) adjustment of structure and references in accordance with IEC 61558-1:2017;
b) description of constructions moved to IEC 61558-1:2017;
c) new symbol for power supply unit with linearly regulated output voltage.

The text of this International Standard is based on the following documents:

Draft	Report on voting
96/587/FDIS	96/591/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

It has the status of a group safety publication in accordance with IEC Guide 104.

This International Standard is to be used in conjunction with IEC 61558-1:2017.

This document supplements or modifies the corresponding clauses in IEC 61558-1:2017, so as to convert that publication into the IEC standard: *Particular requirements and tests for constant voltage transformers and power supply units for constant voltage.*

A list of all parts in the IEC 61558 series published under the general title *Safety of transformers, reactors, power supply units and combinations thereof,* can be found on the IEC website.

Future standards in this series will carry the new general title as cited above. Titles of existing standards in this series will be updated at the time of the next edition.

Where this document states "*addition*", "*modification*" or "*replacement*", the relevant text of IEC 61558-1:2017 is to be adopted accordingly.

In this document, the following print types are used:

– requirements proper: in roman type;

– *test specifications: in italic type*;

– explanatory matter: in smaller roman type:

In the text of this document, the words in **bold** are defined in Clause 3.

Subclauses, notes, figures and tables additional to those in IEC 61558-1:2017 are numbered starting from 101; supplementary annexes are entitled AA, BB, etc.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

INTRODUCTION

IEC TC 96 has a group safety function in accordance with IEC Guide 104 for transformers other than those intended to supply distribution networks, in particular transformers and power supply units intended to allow the application of protective measures against electric shock as defined by TC 64, which is about electrical installations and protection against electric shock, but in certain cases including the limitation of voltage and horizontal safety function for SELV, in accordance with IEC 60364-4-41.

The group safety function (GSF) is used because of responsibility for safety extra-low voltage (SELV) in accordance with IEC 61140:2016, 5.2.6 and IEC 60364-4-41:2005, 414.3.1 or control circuits in accordance with IEC 60204-1:2016, 7.2.4.

The group safety function is used for each part of IEC 61558-2 because different standards of the IEC 61558 series can be combined in one construction but in certain cases with no limitation of rated output power.

For example an auto-transformer in accordance with IEC 61558-2-13 can be designed with a separate SELV-circuit in accordance with the particular requirements for IEC 61558-2-6 relating to the general requirements of IEC 61558-1.

SAFETY OF TRANSFORMERS, REACTORS, POWER SUPPLY UNITS AND COMBINATIONS THEREOF –

Part 2-12: Particular requirements and tests for constant voltage transformers and power supply units for constant voltage

1 Scope

Replacement:

This part of IEC 61558 deals with the safety of **constant voltage transformers** for general applications and **power supply units for constant voltage** for general applications. **Constant voltage transformers** incorporating **electronic circuits** are also covered by this document.

NOTE 1 Safety includes electrical, thermal and mechanical aspects.

Unless otherwise specified, from here onward, the term **transformer** covers **constant voltage transformers** for general applications and **power supply units for constant voltage** for general applications.

This document is applicable to **stationary** or **portable** single-phase or polyphase, air-cooled (natural or forced) **independent** or **associated dry-type**:

– **constant voltage auto-transformers**;
– **constant voltage separating transformers**;
– **constant voltage isolating transformers**;
– **constant voltage safety isolating transformers**.

The windings can be encapsulated or non-encapsulated.

For **power supply units** (linear) this document is applicable. For **switch mode power supply units** IEC 61558-2-16 is applicable together with this document. Where two requirements are in conflict, the most severe take precedence.

The **rated supply voltage** does not exceed 1 000 V AC. The **rated supply frequency** does not exceed 500 Hz, the **internal operating resonant frequency** does not exceed 30 kHz and the **internal operating frequency** does not exceed 100 MHz.

The **rated output** does not exceed:

– 40 kVA for single-phase **constant voltage auto-transformers**;
– 200 kVA for polyphase **constant voltage auto-transformers**;
– 25 kVA for single-phase **constant voltage separating transformers** and **constant voltage isolating transformers**;
– 40 kVA for polyphase **constant voltage separating transformers** and **constant voltage isolating transformers**;
– 10 kVA for single-phase **constant voltage safety isolating transformers**;
– 16 kVA for polyphase **constant voltage safety isolating transformers.**

This document is applicable to **transformers** without limitation of the **rated output**, subject to an agreement between the purchaser and the manufacturer.

NOTE 2 **Transformers** intended to supply distribution networks are not included in the scope.

Where applicable to **constant voltage auto-transformers**

– the **no-load output voltage** or the **rated output voltage** does not exceed 1 000 V AC or 1 415 V ripple-free DC, and for **independent constant voltage auto-transformers** the **no-load output voltage** and the **rated output voltage** exceed 50 V AC or 120 V ripple-free DC;

– **constant voltage auto-transformers** covered by this document are used only in applications where no **insulation** between circuits is required by the installation rules or by the end product standard.

Where applicable to **constant voltage separating transformers**

– the **no-load output voltage** or the **rated output voltage** does not exceed 1 000 V AC or 1 415 V ripple-free DC, and for **independent constant voltage separating transformers** the **no-load output voltage** and the **rated output voltage** exceed 50 V AC or 120 V ripple-free DC;

– **constant voltage separating transformers** covered by this document are used only in applications where **double** or **reinforced insulation** between circuits is not required by the installation rules or by the end product standard.

Where applicable to **constant voltage isolating transformers**

– the **no-load output voltage** or the **rated output voltage** does exceed 50 V AC or 120 V ripple-free DC and where applicable, does not exceed 500 V AC or 708 V ripple-free DC. The **no-load output voltage** and the **rated output voltage** can be up to 1 000 V AC or 1 415 V ripple-free DC for special applications;

– **constant voltage isolating transformers** covered by this document are used only in applications where **double** or **reinforced insulation** between circuits is required by the installation rules or by the end product standard.

Where applicable to **constant voltage safety isolating transformers**

– the **no-load output voltage** or the **rated output voltage** does not exceed 50 V AC or 120 V ripple-free DC;

– **constant voltage safety isolating transformers** covered by this document are used only in applications where **double** or **reinforced insulation** between circuits is required by the installation rules or by the end product standard.

This document is not applicable to external circuits and their components intended to be connected to the input terminals and output terminals of the **transformers**.

Attention is drawn to the following if necessary:

– for **transformers** intended to be used in vehicles, on board ships, and aircraft, additional requirements (from other applicable standards, national rules, etc.) ;

– measures to protect the **enclosure** and the components inside the enclosure against external influences such as fungus, vermin, termites, solar-radiation, and icing;

– the different conditions for transportation, storage, and operation of the **transformers**;

– additional requirements in accordance with other appropriate standards and national rules may be applicable to **transformers** intended for use in special environments.

Future technological development of **transformers** may necessitate a need to increase the upper limit of the frequencies. Until then this document may be used as a guidance document.

This group safety publication focusing on safety guidance is primarily intended to be used as a product safety standard for the products mentioned in the scope, but is also intended to be used by technical committees in the preparation of publications for products similar to those mentioned in the scope of this group safety publication, in accordance with the principles laid down in IEC Guide 104 and ISO/IEC Guide 51.

One of the responsibilities of a technical committee is, wherever applicable, to make use of basic safety publications and/or group safety publications in the preparation of its publications.

2 Normative references

This clause of IEC 61558-1:2017 is applicable except as follows:

Addition

IEC 61558-1:2017, *Safety of transformers, reactors, power supply units and combinations thereof – Part 1: General requirements and tests*

IEC 61558-2-16:2021, *Safety of transformers, reactors, power supply units and combinations thereof – Part 16: Particular requirements and tests for switch mode power supply units and transformers for switch mode power supply units for general applications*

SOMMAIRE

AVANT-PROPOS 23
INTRODUCTION 26
1 Domaine d'application 27
2 Références normatives 29
3 Termes et définitions 29
4 Exigences générales 30
5 Généralités sur les essais 30
6 Caractéristiques assignées 30
7 Classification 31
8 Marquage et indications 31
9 Protection contre les chocs électriques 33
10 Changement de la tension primaire d'alimentation 33
11 Tension secondaire et courant secondaire en charge 34
12 Tension secondaire à vide 34
13 Tension de court-circuit 35
14 Échauffements 35
15 Protection contre les courts-circuits et les surcharges 36
16 Résistance mécanique 37
17 Protection contre les effets nuisibles dus à la pénétration de poussière, d'objets solides et de l'humidité 37
18 Résistance d'isolement, rigidité diélectrique et courant de fuite 37
19 Construction 38
20 Composants 38
21 Conducteurs internes 38
22 Raccordement à l'alimentation et câbles souples externes 38
23 Bornes pour conducteurs externes 38
24 Dispositions en vue de la mise à la terre de protection 39
25 Vis et connexions 39
26 Lignes de fuite, distances d'isolement et distances à travers l'isolation 39
27 Résistance à la chaleur, au feu et aux courants de cheminement 39
28 Protection contre la rouille 39
Annexes 40
Annexe L (normative) Essais individuels de série (essais en cours de fabrication) 40
Bibliographie 41

Tableau 101 – Symboles qui indiquent le type de transformateur 32

COMMISSION ÉLECTROTECHNIQUE INTERNATIONALE

_____

SÉCURITÉ DES TRANSFORMATEURS, BOBINES D'INDUCTANCE, BLOCS D'ALIMENTATION ET DES COMBINAISONS DE CES ÉLÉMENTS –

Partie 2-12: Exigences particulières et essais pour les transformateurs à tension constante et les blocs d'alimentation pour tension constante

AVANT-PROPOS

1) La Commission Électrotechnique Internationale (IEC) est une organisation mondiale de normalisation composée de l'ensemble des comités électrotechniques nationaux (Comités nationaux de l'IEC). L'IEC a pour objet de favoriser la coopération internationale pour toutes les questions de normalisation dans les domaines de l'électricité et de l'électronique. À cet effet, l'IEC – entre autres activités – publie des Normes internationales, des Spécifications techniques, des Rapports techniques, des Spécifications accessibles au public (PAS) et des Guides (ci-après dénommés "Publication(s) de l'IEC"). Leur élaboration est confiée à des comités d'études, aux travaux desquels tout Comité national intéressé par le sujet traité peut participer. Les organisations internationales, gouvernementales et non gouvernementales, en liaison avec l'IEC, participent également aux travaux. L'IEC collabore étroitement avec l'Organisation Internationale de Normalisation (ISO), selon des conditions fixées par accord entre les deux organisations.
2) Les décisions ou accords officiels de l'IEC concernant les questions techniques représentent, dans la mesure du possible, un accord international sur les sujets étudiés, étant donné que les Comités nationaux de l'IEC intéressés sont représentés dans chaque comité d'études.
3) Les Publications de l'IEC se présentent sous la forme de recommandations internationales et sont agréées comme telles par les Comités nationaux de l'IEC. Tous les efforts raisonnables sont entrepris afin que l'IEC s'assure de l'exactitude du contenu technique de ses publications; l'IEC ne peut pas être tenue responsable de l'éventuelle mauvaise utilisation ou interprétation qui en est faite par un quelconque utilisateur final.
4) Dans le but d'encourager l'uniformité internationale, les Comités nationaux de l'IEC s'engagent, dans toute la mesure possible, à appliquer de façon transparente les Publications de l'IEC dans leurs publications nationales et régionales. Toutes divergences entre toutes Publications de l'IEC et toutes publications nationales ou régionales correspondantes doivent être indiquées en termes clairs dans ces dernières.
5) L'IEC elle-même ne fournit aucune attestation de conformité. Des organismes de certification indépendants fournissent des services d'évaluation de conformité et, dans certains secteurs, accèdent aux marques de conformité de l'IEC. L'IEC n'est responsable d'aucun des services effectués par les organismes de certification indépendants.
6) Tous les utilisateurs doivent s'assurer qu'ils sont en possession de la dernière édition de cette publication.
7) Aucune responsabilité ne doit être imputée à l'IEC, à ses administrateurs, employés, auxiliaires ou mandataires, y compris ses experts particuliers et les membres de ses comités d'études et des Comités nationaux de l'IEC, pour tout préjudice causé en cas de dommages corporels et matériels, ou de tout autre dommage de quelque nature que ce soit, directe ou indirecte, ou pour supporter les coûts (y compris les frais de justice) et les dépenses découlant de la publication ou de l'utilisation de cette Publication de l'IEC ou de toute autre Publication de l'IEC, ou au crédit qui lui est accordé.
8) L'attention est attirée sur les références normatives citées dans cette publication. L'utilisation de publications référencées est obligatoire pour une application correcte de la présente publication.
9) L'IEC attire l'attention sur le fait que la mise en application du présent document peut entraîner l'utilisation d'un ou de plusieurs brevets. L'IEC ne prend pas position quant à la preuve, à la validité et à l'applicabilité de tout droit de brevet revendiqué à cet égard. À la date de publication du présent document, l'IEC n'a pas reçu notification qu'un ou plusieurs brevets pouvaient être nécessaires à sa mise en application. Toutefois, il y a lieu d'avertir les responsables de la mise en application du présent document que des informations plus récentes sont susceptibles de figurer dans la base de données de brevets, disponible à l'adresse https://patents.iec.ch. L'IEC ne saurait être tenue pour responsable de l'identification de ces droits de propriété en tout ou partie.

L'IEC 61558-2-12 a été établie par le comité d'études 96 de l'IEC: Transformateurs, bobines d'inductance, blocs d'alimentation et combinaisons de ces éléments. Il s'agit d'une Norme internationale.

Cette troisième édition annule et remplace la deuxième édition parue en 2011. Cette édition constitue une révision technique.

Cette édition inclut les modifications techniques majeures suivantes par rapport à l'édition précédente:

a) la structure et les références ont été alignées sur l'IEC 61558-1:2017;

b) la description des constructions a été déplacée dans l'IEC 61558-1:2017;

c) un nouveau symbole a été ajouté pour les blocs d'alimentation dont la régulation de la tension secondaire est linéaire.

Le texte de cette Norme internationale est issu des documents suivants:

Projet	Rapport de vote
96/587/FDIS	96/591/RVD

Le rapport de vote indiqué dans le tableau ci-dessus donne toute information sur le vote ayant abouti à son approbation.

La langue employée pour l'élaboration de cette Norme internationale est l'anglais.

Le présent document a été rédigé selon les Directives ISO/IEC, Partie 2, il a été développé selon les Directives ISO/IEC, Partie 1 et les Directives ISO/IEC, Supplément IEC, disponibles sous www.iec.ch/members_experts/refdocs. Les principaux types de documents développés par l'IEC sont décrits plus en détail sous www.iec.ch/standardsdev/publications.

Il a le statut de publication groupée de sécurité conformément au Guide 104 de l'IEC.

La présente Norme internationale doit être utilisée conjointement avec l'IEC 61558-1:2017.

Le présent document complète ou modifie les articles correspondants de l'IEC 61558-1:2017, de façon à transformer cette publication en norme IEC: *Exigences particulières et essais pour les transformateurs à tension constante et les blocs d'alimentation pour tension constante*.

Une liste de toutes les parties de la série IEC 61558, publiées sous le titre général *Sécurité des transformateurs, bobines d'inductance, blocs d'alimentation et des combinaisons de ces éléments*, se trouve sur le site web de l'IEC.

Les futures normes de cette série porteront le nouveau titre général cité ci-dessus. Le titre des normes qui existent déjà dans cette série sera mis à jour lors de leur prochaine édition.

Lorsque le présent document mentionne "*addition*", "*modification*" ou "*remplacement*", le texte correspondant de l'IEC 61558-1:2017 doit être adapté en conséquence.

Dans le présent document, les caractères d'imprimerie suivants sont utilisés:

– exigences proprement dites: caractères romains;

– *modalités d'essais: caractères italiques*;

– commentaires: petits caractères romains.

Dans le texte du présent document, les termes en **gras** sont définis à l'Article 3.

Les paragraphes, notes, figures et tableaux qui s'ajoutent à ceux de l'IEC 61558-1:2017 sont numérotés à partir de 101; les annexes qui sont ajoutées sont désignées AA, BB, etc.

Le comité a décidé que le contenu du présent document ne sera pas modifié avant la date de stabilité indiquée sur le site web de l'IEC sous webstore.iec.ch dans les données relatives au document recherché. À cette date, le présent document sera

- reconduit,
- supprimé, ou
- révisé.

INTRODUCTION

Le CE 96 de l'IEC a une fonction groupée de sécurité, conformément au Guide 104 de l'IEC relatif aux transformateurs autres que ceux destinés à alimenter les réseaux de distribution, notamment les transformateurs et les blocs d'alimentation destinés à permettre l'application de mesures de protection contre les chocs électriques, comme cela est défini par le CE 64, qui traite des installations électriques et de la protection contre les chocs électriques, mais qui incluent également dans certains cas la limitation de la tension et de la fonction de sécurité horizontale pour la TBTS, conformément à l'IEC 60364-4-41.

La fonction groupée de sécurité (GSF, *Group Safety Function*) est utilisée en raison de la responsabilité de la très basse tension de sécurité (TBTS), conformément au 5.2.6 de l'IEC 61140:2016 et au 414.3.1 de l'IEC 60364-4-41:2005, ou des circuits de commande, conformément au 7.2.4 de l'IEC 60204-1:2016.

La fonction groupée de sécurité est utilisée pour chacune des parties de l'IEC 61558-2, car différentes normes de la série IEC 61558 peuvent être combinées en une seule et même construction, mais dans certains cas sans aucune limitation de la puissance secondaire assignée.

Un autotransformateur conforme à l'IEC 61558-2-13 peut par exemple être conçu avec un circuit TBTS distinct, conformément aux exigences particulières de l'IEC 61558-2-6 liées aux exigences générales de l'IEC 61558-1.

SÉCURITÉ DES TRANSFORMATEURS, BOBINES D'INDUCTANCE, BLOCS D'ALIMENTATION ET DES COMBINAISONS DE CES ÉLÉMENTS –

Partie 2-12: Exigences particulières et essais pour les transformateurs à tension constante et les blocs d'alimentation pour tension constante

1 Domaine d'application

Remplacement:

La présente partie de l'IEC 61558 traite de la sécurité des **transformateurs à tension constante** pour applications d'ordre général et des **blocs d'alimentation pour tension constante** pour applications d'ordre général. Les **transformateurs à tension constante** qui incorporent des **circuits électroniques** sont également couverts par le présent document.

NOTE 1 La sécurité comprend les aspects électriques, thermiques et mécaniques.

Sauf spécification contraire, dans la suite du document, le terme **transformateur** couvre les **transformateurs à tension constante** pour applications d'ordre général et les **blocs d'alimentation pour tension constante** pour applications d'ordre général.

Le présent document s'applique aux **transformateurs de type sec fixes** ou **mobiles**, monophasés ou polyphasés, à refroidissement par air (naturel ou forcé) **indépendants** ou **associés**:

– **autotransformateurs à tension constante**;
– **transformateurs à tension constante à enroulements séparés**;
– **transformateurs à tension constante de séparation des circuits**;
– **transformateurs à tension constante de sécurité**.

Les enroulements peuvent être enrobés ou non enrobés.

Pour les **blocs d'alimentation** (linéaires), le présent document s'applique. Pour les **blocs d'alimentation à découpage**, l'IEC 61558-2-16 et le présent document s'appliquent. Lorsque deux exigences sont contradictoires, la plus contraignante prévaut.

La **tension primaire assignée** ne dépasse pas 1 000 V en courant alternatif. La **fréquence d'alimentation assignée** ne dépasse pas 500 Hz, la **fréquence de résonance de fonctionnement interne** ne dépasse pas 30 kHz et la **fréquence de fonctionnement interne** ne dépasse pas 100 MHz.

La **puissance assignée** ne dépasse pas:

– 40 kVA pour les **autotransformateurs à tension constante** monophasés;
– 200 kVA pour les **autotransformateurs à tension constante** polyphasés;
– 25 kVA pour les **transformateurs à tension constante à enroulements séparés** et les **transformateurs à tension constante de séparation des circuits** monophasés;
– 40 kVA pour les **transformateurs à tension constante à enroulements séparés** et les **transformateurs à tension constante de séparation des circuits** polyphasés;
– 10 kVA pour les **transformateurs à tension constante de sécurité** monophasés;
– 16 kVA pour les **transformateurs à tension constante de sécurité** polyphasés.

Le présent document s'applique aux **transformateurs** sans limitation de la **puissance assignée**, qui font l'objet d'un accord entre l'acheteur et le fabricant.

NOTE 2 Le domaine d'application ne couvre pas les **transformateurs** destinés à alimenter les réseaux de distribution.

Quand cela s'applique aux **autotransformateurs à tension constante**

– la **tension secondaire à vide** ou la **tension secondaire assignée** ne dépasse pas 1 000 V en courant alternatif ou 1 415 V en courant continu lissé et, pour les **autotransformateurs à tension constante indépendants**, la **tension secondaire à vide** et la **tension secondaire assignée** dépassent 50 V en courant alternatif ou 120 V en courant continu lissé;
– les **autotransformateurs à tension constante** couverts par le présent document ne sont utilisés que dans le cadre d'applications pour lesquelles les règles d'installation ou la norme du produit final n'exigent aucune **isolation** entre les circuits.

Quand cela s’applique aux **transformateurs à tension constante à enroulements séparés**

– la **tension secondaire à vide** ou la **tension secondaire assignée** ne dépasse pas 1 000 V en courant alternatif ou 1 415 V en courant continu lissé et, pour les **transformateurs à tension constante à enroulements séparés indépendants**, la **tension secondaire à vide** et la **tension secondaire assignée** dépassent 50 V en courant alternatif ou 120 V en courant continu lissé;
– les **transformateurs à tension constante à enroulements séparés** couverts par le présent document ne sont utilisés que dans le cadre d'applications pour lesquelles les règles d'installation ou la norme du produit final n'exigent aucune **isolation double** ou **renforcée** entre les circuits.

Quand cela s'applique aux **transformateurs à tension constante de séparation des circuits**

– la **tension secondaire à vide** ou la **tension secondaire assignée** dépasse 50 V en courant alternatif ou 120 V en courant continu lissé et, le cas échéant, ne dépasse pas 500 V en courant alternatif ou 708 V en courant continu lissé. La **tension secondaire à vide** et la **tension secondaire assignée** peuvent atteindre 1 000 V en courant alternatif ou 1 415 V en courant continu lissé pour des applications spéciales;
– les **transformateurs à tension constante de séparation des circuits** couverts par le présent document ne sont utilisés que dans le cadre d'applications pour lesquelles les règles d'installation ou la norme du produit final exigent une **isolation double** ou **renforcée** entre les circuits.

Quand cela s’applique aux **transformateurs à tension constante de sécurité**

– la **tension secondaire à vide** ou la **tension secondaire assignée** ne dépasse pas 50 V en courant alternatif ou 120 V en courant continu lissé;
– les **transformateurs à tension constante de sécurité** couverts par le présent document ne sont utilisés que dans le cadre d'applications pour lesquelles les règles d'installation ou la norme du produit final exigent une **isolation double** ou **renforcée** entre les circuits.

Le présent document ne s'applique pas aux circuits externes et à leurs composants destinés à être connectés aux bornes primaires et bornes secondaires des **transformateurs**.

L'attention est attirée sur les points suivants, si nécessaire:

– exigences supplémentaires (issues d'autres normes applicables, règles nationales, etc.) pour les **transformateurs** destinés à être utilisés dans des véhicules, à bord de navires ou d'avions;
– des mesures visent à protéger l'**enveloppe** et les composants situés à l'intérieur de celle-ci contre les facteurs d'influence externes comme les champignons, la vermine, les termites, les rayonnements solaires et le givre;

– différentes conditions de transport, de stockage et de fonctionnement pour les **transformateurs**;
– exigences supplémentaires qui peuvent s'appliquer aux **transformateurs** destinés à être utilisés dans un environnement particulier, au regard d'autres normes et règles nationales applicables.

Les évolutions techniques futures des **transformateurs** peuvent nécessiter une augmentation de la limite supérieure des fréquences. En attendant, le présent document peut être utilisé à titre de recommandation.

La présente publication groupée de sécurité portant sur des recommandations de sécurité est avant tout destinée à être utilisée en tant que norme en matière de sécurité des produits pour les produits cités dans le domaine d'application, mais elle est également destinée à être utilisée par les comités d'études dans le cadre de l'élaboration de publications pour des produits similaires à ceux cités dans le domaine d'application de la présente publication groupée de sécurité, conformément aux principes établis dans le Guide 104 de l'IEC et le Guide 51 de l'ISO/IEC.

L'une des responsabilités d'un comité d'études consiste, le cas échéant, à utiliser les publications fondamentales de sécurité et/ou les publications groupées de sécurité dans le cadre de l'élaboration de ses publications.

2 Références normatives

L'article de l'IEC 61558-1:2017 s'applique avec les exceptions suivantes:

Addition:

IEC 61558-1:2017, *Sécurité des transformateurs, bobines d'inductance, blocs d'alimentation et des combinaisons de ces éléments – Partie 1: Exigences générales et essais*

IEC 61558-2-16:2021, *Sécurité des transformateurs, bobines d'inductance, blocs d'alimentation et combinaisons de ces éléments – Partie 2-16: Exigences particulières et essais pour les blocs d'alimentation à découpage et les transformateurs pour blocs d'alimentation à découpage pour applications d'ordre général*