IEC 63305

Edition 1.0 2024-02

INTERNATIONAL STANDARD

NORME INTERNATIONALE

colour inside

Underwater acoustics – Calibration of acoustic wave vector receivers in the frequency range 5 Hz to 10 kHz

Acoustique sous-marine – Étalonnage des récepteurs vectoriels d'ondes acoustiques dans la plage de fréquences de 5 Hz à 10 kHz



IEC 63305:2024-02(en-fr)



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2024 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Secretariat
3, rue de Varembé
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC
The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications
The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform
The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, …). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished
Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc
If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch
Discover our powerful search engine and read freely all the publications previews, graphical symbols and the glossary. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org
The world's leading online dictionary on electrotechnology, containing more than 22 500 terminological entries in English and French, with equivalent terms in 25 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

A propos de l'IEC
La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC
Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Recherche de publications IEC - webstore.iec.ch/advsearchform
La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études, …). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished
Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et une fois par mois par email.

Service Clients - webstore.iec.ch/csc
Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch
Découvrez notre puissant moteur de recherche et consultez gratuitement tous les aperçus des publications, symboles graphiques et le glossaire. Avec un abonnement, vous aurez toujours accès à un contenu à jour adapté à vos besoins.

Electropedia - www.electropedia.org
Le premier dictionnaire d'électrotechnologie en ligne au monde, avec plus de 22 500 articles terminologiques en anglais et en français, ainsi que les termes équivalents dans 25 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

IEC 63305

Edition 1.0 2024-02

INTERNATIONAL STANDARD

NORME INTERNATIONALE

colour inside

Underwater acoustics – Calibration of acoustic wave vector receivers in the frequency range 5 Hz to 10 kHz

Acoustique sous-marine – Étalonnage des récepteurs vectoriels d'ondes acoustiques dans la plage de fréquences de 5 Hz à 10 kHz

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 17.140.50

ISBN 978-2-8322-8123-9

Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.

® Registered trademark of the International Electrotechnical Commission
Marque déposée de la Commission Electrotechnique Internationale

CONTENTS

FOREWORD 5
INTRODUCTION 7
1 Scope 8
2 Normative references 8
3 Terms and definitions 8
4 List of symbols 14
5 Relationship of vector quantities in sound field 16
6 General procedures for calibration 17
6.1 General calibration requirements 17
6.1.1 Types of calibration 17
6.1.2 Acoustic field requirements 17
6.2 Acoustic standing wave tube requirements 18
6.2.1 Requirements for standing wave tube [8] 18
6.2.2 Requirements for immersed depth of transducers 19
6.3 Acoustic travelling wave tube requirements 20
6.3.1 Requirements for driving signal 20
6.3.2 Requirements for the travelling wave tube 20
6.4 Equipment requirements 20
6.4.1 Calibration facility 20
6.4.2 Instrumentation 21
6.5 Positioning and alignment 23
6.5.1 Coordinate system 23
6.5.2 Reference direction 23
6.5.3 Transducer mounting and support 23
6.5.4 Alignment 24
6.6 Representation of the frequency response 25
6.7 Frequency limitations 25
6.7.1 High-frequency limit 25
6.7.2 Low frequency limit 25
6.8 Checks for acoustic interference 26
7 Electrical measurements 26
7.1 Signal type 26
7.2 Electrical earthing 26
7.3 Measurement of transducer output voltage 26
7.3.1 General 26
7.3.2 Signal analysis 27
7.3.3 Electrical loading by measuring instrument 27
7.3.4 Electrical loading by extension cables 27
7.3.5 Electrical noise 27
7.3.6 Cross-talk 28
7.3.7 Integral preamplifiers 28
7.4 Measurement of projector drive current 28
7.4.1 Instrumentation 28
7.4.2 Signal analysis 28
8 Preparation of measurement 28
8.1 Preparation of transducers 28

8.1.1 Soaking 28
8.1.2 Wetting 29
8.2 Environmental conditions (temperature and depth) 29
9 Free-field calibration 29
9.1 Free-field reciprocity calibration 29
9.1.1 General 29
9.1.2 Principle 30
9.1.3 Measurement 32
9.1.4 Uncertainty 32
9.2 Free-field calibration using optical interferometry 32
9.2.1 General 32
9.2.2 Principle 32
9.2.3 Measurement 33
9.2.4 Uncertainty 34
9.3 Free-field calibration using a reference hydrophone 34
9.3.1 General 34
9.3.2 Principle 34
9.3.3 Measurement 35
9.3.4 Uncertainty 35
10 Calibration in standing wave tube 35
10.1 Calibration using reference accelerometer 35
10.1.1 General 35
10.1.2 Principle 35
10.1.3 Measurement 37
10.1.4 Uncertainty 37
10.2 Comparison calibration using reference hydrophone in standing wave tube 37
10.2.1 General 37
10.2.2 Principle 37
10.2.3 Measurement 39
10.2.4 Uncertainty 39
10.3 Horizontal standing wave tube calibration 39
10.3.1 General 39
10.3.2 Principle 39
10.3.3 Measurement 41
10.3.4 Uncertainty 41
10.4 Calibration using optical interferometry in standing wave tube 41
10.4.1 General 41
10.4.2 Principle 41
10.4.3 Measurement 43
10.4.4 Uncertainty 43
11 Calibration in a travelling wave tube 43
11.1 General 43
11.2 Principle 44
11.2.1 General 44
11.2.2 Establishment of a unidirectional, plane progressive wave field 45
11.2.3 Sensitivity calculations 48
11.2.4 Uncertainty 48
12 Reporting of results 48

12.1 Sensitivity 48
12.2 Sensitivity level 49
12.3 Environmental considerations for calibration 49
12.4 Calibration uncertainties 49
12.5 Auxiliary metadata 49
13 Recalibration periods 50
Annex A (informative) Directional response of a vector receiver 51
A.1 General principle 51
A.2 Types of measurement implementation 51
A.3 Coordinate system 51
A.4 Measurement of vector receiver directional response 51
A.5 Calculation of angular deviation loss 52
A.6 Uncertainty 52
Annex B (informative) Inertial vector receiver calibration using optical interferometry in air 53
B.1 General 53
B.2 Principle 53
B.3 Procedure 53
B.4 Discussion 55
Annex C (informative) Assessment of uncertainty of vector receiver calibration 56
C.1 General 56
C.2 Type A evaluation of uncertainty 56
C.3 Type B evaluation of uncertainty 56
C.4 Reported uncertainty 56
C.5 Common sources of uncertainty 57
Bibliography 60

Figure 1 – The structure of the calibration chamber 19
Figure 2 – Co-vibrating vector receiver suspended on a mounting ring 24
Figure 3 – Measurement framework for free-field reciprocity calibration of the vector receiver 30
Figure 4 – Schematic diagram of free-field calibration for vector receiver using an optical interferometer 33
Figure 5 – Schematic diagram of free-field comparison calibration for vector receiver using reference hydrophone 34
Figure 6 – Schematic diagram of vertical standing wave tube calibration using reference accelerometer 36
Figure 7 – Schematic diagram of vertical standing wave tube calibration using reference hydrophone 38
Figure 8 – Schematic diagram of calibration principle and horizontal standing wave tube calibration 40
Figure 9 – Schematic diagram of calibration for vector receiver using optical interferometer in standing wave tube 42
Figure 10 – Schematic diagram of calibration for vector receiver in a travelling wave tube 44
Figure B.1 – Schematic diagram of calibration using optical interferometer in air for inertial vector receiver 54

INTERNATIONAL ELECTROTECHNICAL COMMISSION

_____

UNDERWATER ACOUSTICS – CALIBRATION OF ACOUSTIC WAVE VECTOR RECEIVERS IN THE FREQUENCY RANGE 5 Hz TO 10 kHz

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at https://patents.iec.ch. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 63305 has been prepared by IEC technical committee 87: Ultrasonics. It is an International Standard.

The text of this International Standard is based on the following documents:

Draft	Report on voting
87/839/FDIS	87/843/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

NOTE Words in **bold** in the text are defined in Clause 3.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn, or
- revised.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

Unlike traditional piezoelectric **hydrophones** which are sensitive to sound pressure, **vector receivers** measure **sound particle** motion (velocity, acceleration or displacement) or **sound pressure gradient**, and have strongly **directional response** in their working frequency range. The calibration of these **vector receivers** which measure **sound particle** motion or **sound pressure gradient** is considered in this document.

The output voltage of a **vector receiver** channel to be calibrated is proportional to the **sound particle** motion or **sound pressure gradient** at the reference centre of the receiver. The directivity of the **vector receiver** channel is independent of acoustical frequency, and the ratio of the output voltage of the receiver channel at angle θ to the maximum output voltage on the axial direction is equal to $|\cos\theta|$ [1][1].

Recent developments of **acoustic wave vector receivers** for ocean acoustics, such as those that measure **sound particle velocity**, have led to a number of commercial systems being made available on the market. In addition to providing sensors which possess some useful directivity for low-frequency applications, they are increasingly used for measurement of underwater noise exposure for marine fauna that are sensitive to sound particle motion rather than sound pressure (for example, fish and invertebrates). However, calibration of such sensors poses technical challenges, and is not covered by the existing international standards such as IEC 60565 [2], [3]. Building on work begun in China and Russia [4], where a successful bilateral comparison has recently been concluded, this work establishes an International Standard on calibration of **vector receivers** in the frequency range 5 Hz to 10 kHz.

[1] Numbers in square brackets refer to the Bibliography.

UNDERWATER ACOUSTICS – CALIBRATION OF ACOUSTIC WAVE VECTOR RECEIVERS IN THE FREQUENCY RANGE 5 Hz TO 10 kHz

1 Scope

Usually, **acoustic wave vector receivers** are designed and constructed based on one of two principles. One is the sound pressure difference (gradient) principle. When measuring with this sensor, the **vector receiver** is rigidly fixed on a mount and supported in water. The other is the co-vibrating (**inertial**) principle. When measuring with this sensor, the **vector receiver** is suspended on a mount and supported in water in a non-rigid manner, which allows the **vector receiver** co-vibrate in the same direction as the **sound particle** in the sound wave field.

Many methods have been used to calibrate **vector receivers**, such as free-field calibration, calibration in standing wave tube and calibration in a travelling wave tube. This document specifies methods and procedures for calibration of **vector receivers** in the frequency range 5 Hz to 10 kHz, which are applicable to **vector receivers** based on the two different principles. In addition, it describes an absolute method of **inertial vector receiver** calibration in air using optical interferometry.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60500:2017, *Underwater acoustics – Hydrophones – Properties of hydrophones in the frequency range 1 Hz to 500 kHz*

IEC 60565-1:2020, *Underwater acoustics – Hydrophones – Calibration of hydrophones, Part 1: Procedures for free-field calibration of hydrophones*

ISO 80000-8:2020, *Quantities and units – Part 8: Acoustics*

ISO 18405:2017, *Underwater acoustics – Terminology*

ISO/IEC Guide 98-3, *Uncertainty of measurement – Part 3: Guide to the expression of uncertainty in measurement*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60500:2017, IEC 60565-1:2020, ISO 80000-8:2020, ISO 18405:2017 and the following apply.

ISO and IEC maintain terminology databases for use in standardization at the following addresses:

- IEC Electropedia: available at https://www.electropedia.org/
- ISO Online browsing platform: available at https://www.iso.org/obp

3.1
sound particle
material element
smallest element of the medium that represents the medium's mean density

[SOURCE: ISO 80000-8:2020, 3.1]

3.2
sound particle displacement
δ
displacement of a **sound particle** caused by the action of sound

Note 1 to entry: **Sound particle displacement** is a function of time, t, which is indicated by means of an argument t, as in $\boldsymbol{\delta}(t)$.

Note 2 to entry: **Sound particle displacement** is expressed in metres, m.

Note 3 to entry: **Sound particle displacement** is a vector quantity. Spatial components of the **sound particle displacement** can be indicated by assigning subscripts to the symbol. For example, in Cartesian coordinates, $\boldsymbol{\delta} = (\delta_x,\delta_y,\delta_z)$. By convention in underwater acoustics, the z axis is usually chosen to point vertically down from the sea surface, with x and y axes in the horizontal plane. If the **sound particle displacement** is in the same direction in which the sound wave propagates, its symbol can be simply δ.

[SOURCE: ISO 18405:2017, 3.1.2.9, modified – In the definition, "material element" has been replaced by "sound particle".]

3.3
sound particle velocity
u
contribution to velocity of a **sound particle** caused by the action of sound

Note 1 to entry: **Sound particle velocity** is a function of time, t, which is indicated by means of an argument t, as in $\boldsymbol{u}(t)$.

Note 2 to entry: For small-amplitude sound waves in an otherwise stationary medium, the **sound particle velocity** and **sound particle displacement** are related by

$$\boldsymbol{u}(t) = \frac{\partial \boldsymbol{\delta}(t)}{\partial t} \tag{1}$$

where $\boldsymbol{\delta}(t)$ is the **sound particle displacement** at time, t, and the partial derivative is evaluated at a fixed position.

Note 3 to entry: **Sound particle velocity** is expressed in units of metre per second, $\mathrm{m \cdot s^{-1}}$.

Note 4 to entry: **Sound particle velocity** is a vector quantity. Spatial components of the **sound particle velocity** can be indicated by assigning subscripts to the symbol. For example, in Cartesian coordinates, $\boldsymbol{u} = (u_x,u_y,u_z)$. By convention in underwater acoustics, the z axis is usually chosen to point vertically down from the sea surface, with x and y axes in the horizontal plane. If the **sound particle velocity** is in the same direction in which the sound wave propagates, its symbol can be simply u.

[SOURCE: ISO 18405:2017, 3.1.2.10, modified – In the definition, "material element" has been replaced by "sound particle".]

3.4
sound particle acceleration
a
contribution to acceleration of a **sound particle** caused by the action of sound

Note 1 to entry: **Sound particle acceleration** is a function of time, t, which is indicated by means of an argument t, as in $\boldsymbol{a}(t)$.

Note 2 to entry: For small-amplitude sound waves in an otherwise stationary medium, the **sound particle acceleration** and **sound particle velocity** are related by

$$\boldsymbol{a}(t) = \frac{\partial \boldsymbol{u}(t)}{\partial t} \tag{2}$$

where $\boldsymbol{u}(t)$ is the **sound particle velocity** at time, t, and the partial derivative is evaluated at a fixed position.

Note 3 to entry: **Sound particle acceleration** is expressed in units of metre per second squared, $m \cdot s^{-2}$.

Note 4 to entry: **Sound particle acceleration** is a vector quantity. Spatial components of the **sound particle acceleration** can be indicated by assigning subscripts to the symbol. For example, in Cartesian coordinates, $\boldsymbol{a} = (a_x, a_y, a_z)$. By convention in underwater acoustics, the z axis is usually chosen to point vertically down from the sea surface, with x and y axes in the horizontal plane. If the **sound particle acceleration** is in the same direction in which the sound wave propagates, its symbol can be simply a.

[SOURCE: ISO 18405:2017, 3.1.2.11, modified – In the definition, "material element" has been replaced by "sound particle".]

3.5
sound pressure gradient
∇p

spatial derivative of sound pressure with respect to distance caused by the action of sound

Note 1 to entry: **Sound pressure gradient** is expressed in units of pascal per metre, $Pa \cdot m^{-1}$.

Note 2 to entry: **Sound pressure gradient** is a vector quantity. In Cartesian coordinates, spatial components of the **sound pressure gradient** can be indicated as $\nabla p = (\partial p / \partial x, \partial p / \partial y, \partial p / \partial z)$. By convention in underwater acoustics, the z axis is usually chosen to point vertically down from the sea surface, with x and y axes in the horizontal plane.

3.6
vector receiver
acoustic wave vector receiver
receiving transducer whose output voltage of its receiving channel is proportional to the **sound particle** motion (displacement, velocity or acceleration) or **sound pressure gradient** on the position of the reference centre of it in water

Note 1 to entry: Due to the different constructions, the **vector receiver** can be one-dimensional **vector receiver**, two-dimensional orthogonal **vector receiver** or three-dimensional orthogonal **vector receiver**, and it has different receiving channels. For a three-dimensional orthogonal **vector receiver**, the channels are usually named as x-channel, y-channel and z-channel.

Note 2 to entry: The receiving channel of the **vector receiver** has very strong **directional response**, which is independent of the frequency.

Note 3 to entry: According to the vector values which are perceived, there are different **vector receivers**, including **inertial vector receiver** and **sound pressure gradient receiver**.

Note 4 to entry: Sometimes, the **vector receiver** has a sound pressure (scalar) receiving channel, and open-circuit voltage of the sound pressure channel is proportional to the sound pressure on the position of the reference centre of the **vector receiver**.

Note 5 to entry: The phase of the output signal of the vector receiving channel changes by 180 degrees when the direction of sound wave incidence changes to the opposite direction, which can be found using the output signal of a sound pressure receiving channel as a reference signal when the **vector receiver** has a sound pressure receiving channel in it.

3.7
inertial vector receiver
receiving transducer that senses **sound particle** motion by measuring the reaction of a proof mass in response to motion of the sensor body (e.g. accelerometer, geophone)

3.8
hydrophone
electroacoustic transducer that produces electrical voltages in response to water borne sound pressure signals

[SOURCE: IEC 60500:2017, 3.17, modified – In the definition, "electrical signals" has been replaced with "electrical voltages", and "pressure signals" with "sound pressure signals".]

3.9
sound pressure gradient receiver
receiving transducer that senses the gradient of sound pressure using two or more **hydrophones** separated by distances that are small relative to the wavelength

3.10
directional response
<of a **vector receiver** channel> description of the response of a **vector receiver** channel, as a function of the direction of propagation of the incident plane sound wave, in a given channel direction through the reference centre, at a specified frequency

Note 1 to entry: The **directional response** pattern is usually presented in the form of a two-dimensional polar graph. The scale of the polar can be in terms of sensitivity level or in angular deviation loss (see Annex A).

Note 2 to entry: The **directional response** pattern of the **vector receiver** channel is a cosine function, that is the ratio of the output voltage of the **vector receiver** channel in the direction of angle θ to the maximum output voltage in the axial direction is equal to $\left|\cos\theta\right|$.

[SOURCE: IEC 60500:2017, 3.4, modified – In the definition, "hydrophone" has been replaced with "vector receiver channel", "a specified plane" has been replaced with "a given channel direction", and ", generally presented graphically," has been deleted.]

3.11
axial angular deviation loss
larger value of **directional response** of a **vector receiver** channel on the principal axis minus another value of **directional response** on the symmetrical direction

Note 1 to entry: The **axial angular deviation loss** is expressed as a level in decibels, dB (see Annex A).

Note 2 to entry: Sometimes, the **axial angular deviation loss** is named as asymmetry or maximum heterogeneity of **directional response** on the principal axis of a **vector receiver** channel.

3.12
lateral angular deviation loss
larger value of **directional response** of a **vector receiver** channel on the principal axis minus the smaller value of **directional response** on the lateral axis

Note 1 to entry: The **lateral angular deviation loss** is expressed as a level in decibels, dB (see Annex A).

3.13
sound particle displacement sensitivity
$\underline{M}_{\delta}$
<of a **vector receiver** channel> quotient of the Fourier transform of the output voltage signal $\mathcal{F}\left(U_{\mathrm{VR}}(t)\right)$ of a **vector receiver** channel to the Fourier transform of the **sound particle displacement** signal $\mathcal{F}\left(\delta(t)\right)$, for specified frequency and specified direction of plane wave sound incidence on the position of the reference centre of the **vector receiver** in the undisturbed free field if the **vector receiver** was removed

$$\underline{M}_{\delta} = \frac{\mathcal{F}\left(U_{\mathrm{VR}}(t)\right)}{\mathcal{F}\left(\delta(t)\right)} \tag{3}$$

Note 1 to entry: The **sound particle displacement sensitivity** of a **vector receiver** is a complex-valued parameter. The **sound particle displacement sensitivity** calculated by this equation is in the direction of the sound wave propagation. This calibration procedure can be performed for only one aligned channel, and each channel of the **vector receiver** is calibrated independently.

Note 2 to entry: The modulus of the **sound particle displacement sensitivity** is expressed in units of volt per metre, $\mathrm{V \cdot m^{-1}}$.

Note 3 to entry: The phase angle of the **sound particle displacement sensitivity** is expressed in radians and represents the phase difference between the output voltage of a **vector receiver** and the **sound particle displacement** (see IEC 60500).

3.14
sound particle displacement sensitivity level

$L_{\mathrm{M},\delta}$

twenty times the logarithm to the base 10 of the ratio of the modulus of the **sound particle displacement sensitivity** $\left|\underline{M}_{\delta}\right|$ of a **vector receiver** channel to a reference value of sensitivity, $M_{\delta,\mathrm{ref}}$, in decibels

$$L_{\mathrm{M},\delta} = 20 \log_{10} \frac{\left|\underline{M}_{\delta}\right|}{M_{\delta,\mathrm{ref}}} \ \mathrm{dB} \tag{4}$$

Note 1 to entry: The unit of **sound particle displacement sensitivity level** is expressed as a level in decibels, dB.

Note 2 to entry: The reference value of sensitivity, $M_{\delta,\mathrm{ref}}$, is $1\ \mathrm{V \cdot pm^{-1}}$.

3.15
sound particle velocity sensitivity

$\underline{M}_{\mathrm{u}}$

<of a **vector receiver** channel> quotient of the Fourier transform of the output voltage signal $\mathcal{F}\left(U_{\mathrm{VR}}(t)\right)$ of a **vector receiver** channel to the Fourier transform of the **sound particle velocity** signal $\mathcal{F}\left(u(t)\right)$, for specified frequency and specified direction of plane wave sound incidence on the position of the reference centre of the **vector receiver** in the undisturbed free field if the **vector receiver** was removed

$$\underline{M}_{\mathrm{u}} = \frac{\mathcal{F}\left(U_{\mathrm{VR}}(t)\right)}{\mathcal{F}\left(u(t)\right)} \tag{5}$$

Note 1 to entry: The **sound particle velocity sensitivity** of **vector receivers** is a complex-valued parameter. The **sound particle velocity sensitivity** calculated by this equation is in the direction of the sound wave propagation. This calibration procedure can be performed for only one aligned channel, and each channel of the **vector receiver** is calibrated independently.

Note 2 to entry: The modulus of the **sound particle velocity sensitivity** is expressed in units of volt second per metre, $\mathrm{V \cdot s \cdot m^{-1}}$.

Note 3 to entry: The phase angle of the **sound particle velocity sensitivity** is expressed in radians and represents the phase difference between the output voltage of a **vector receiver** and the **sound particle velocity** (see IEC 60500).

3.16
sound particle velocity sensitivity level
$L_{\mathrm{M,u}}$
twenty times the logarithm to the base 10 of the ratio of the modulus of the **sound particle velocity sensitivity** $\left|\underline{M}_{\mathrm{u}}\right|$ of a **vector receiver** channel to a reference value of sensitivity, $M_{\mathrm{u,ref}}$, in decibels

$$L_{\mathrm{M,u}} = 20\log_{10}\frac{\left|\underline{M}_{\mathrm{u}}\right|}{M_{\mathrm{u,ref}}}\ \mathrm{dB} \tag{6}$$

Note 1 to entry: The unit of **sound particle velocity sensitivity level** is expressed as a level in decibels, dB.

Note 2 to entry: The reference value of sensitivity, $M_{\mathrm{u,ref}}$, is 1 $\mathrm{V{\cdot}s{\cdot}nm^{-1}}$.

3.17
sound particle acceleration sensitivity
$\underline{M}_{\mathrm{a}}$
<of a **vector receiver** channel> quotient of the Fourier transform of the output voltage signal $\mathcal{F}\left(U_{\mathrm{VR}}(t)\right)$ of a **vector receiver** channel to the Fourier transform of the **sound particle acceleration** signal $\mathcal{F}\left(a(t)\right)$, for specified frequency and specified direction of plane wave sound incidence on the position of the reference centre of the **vector receiver** in the undisturbed free field if the **vector receiver** was removed

$$\underline{M}_{\mathrm{a}} = \frac{\mathcal{F}\left(U_{\mathrm{VR}}(t)\right)}{\mathcal{F}\left(a(t)\right)} \tag{7}$$

Note 1 to entry: The **sound particle acceleration sensitivity** of **vector receivers** is a complex-valued parameter. The **sound particle acceleration sensitivity** calculated by this equation is in the direction of the sound wave propagation. This calibration procedure can be performed for only one aligned channel, and each channel of the **vector receiver** is calibrated independently.

Note 2 to entry: The modulus of the **sound particle acceleration sensitivity** is expressed in units of volt second squared per metre, $\mathrm{V{\cdot}s^2{\cdot}m^{-1}}$.

Note 3 to entry: The phase angle of the **sound particle acceleration sensitivity** is expressed in radians and represents the phase difference between the output voltage of a **vector receiver** and the **sound particle acceleration** (see IEC 60500).

3.18
sound particle acceleration sensitivity level
$L_{\mathrm{M,a}}$
twenty times the logarithm to the base 10 of the ratio of the modulus of the **sound particle acceleration sensitivity** $\left|\underline{M}_{\mathrm{a}}\right|$ of a **vector receiver** channel to a reference value of sensitivity, $M_{\mathrm{a,ref}}$, in decibels

$$L_{\mathrm{M,a}} = 20\log_{10}\frac{\left|\underline{M}_{\mathrm{a}}\right|}{M_{\mathrm{a,ref}}}\ \mathrm{dB} \tag{8}$$

Note 1 to entry: The unit of **sound particle acceleration sensitivity level** is expressed as a level in decibels (dB).

Note 2 to entry: The reference value of sensitivity, $M_{a,ref}$, is 1 V·s^2·µm^{-1}.

3.19
sound pressure gradient sensitivity
$\underline{M}_{pg}$
<of a **vector receiver** channel> quotient of the Fourier transform of the output voltage signal $\mathcal{F}\left(U_{VR}(t)\right)$ of a **vector receiver** channel to Fourier transform of the **sound pressure gradient** signal $\mathcal{F}(\nabla p(t))$, for specified frequency and specified direction of plane wave sound incidence on the position of the reference centre of the **vector receiver** in the undisturbed free field if the **vector receiver** was removed

$$\underline{M}_{pg} = \frac{\mathcal{F}\left(U_{VR}(t)\right)}{\mathcal{F}\left(\nabla p(t)\right)} \tag{9}$$

Note 1 to entry: The **sound pressure gradient sensitivity** of **vector receivers** is a complex-valued parameter. The **sound pressure gradient sensitivity** calculated by this equation is in the direction of the sound wave propagation. The calibration procedure can be performed for only one aligned channel, and each channel of the **vector receiver** is calibrated independently.

Note 2 to entry: The modulus of the **sound pressure gradient sensitivity** is expressed in units of volt metre per pascal, V·m·Pa^{-1}.

Note 3 to entry: The phase angle of the **sound pressure gradient sensitivity** is expressed in radians and represents the phase difference between the output voltage of a **vector receiver** and the **sound particle velocity** (see IEC 60500).

3.20
sound pressure gradient sensitivity level
$L_{M,pg}$
twenty times the logarithm to the base 10 of the ratio of the modulus of the **sound pressure gradient sensitivity** $\left|\underline{M}_{pg}\right|$ of a **vector receiver** channel to a reference value of sensitivity, $M_{pg,ref}$, in decibels

$$L_{M,pg} = 20\log_{10}\frac{\left|\underline{M}_{pg}\right|}{M_{pg,ref}}\ \text{dB} \tag{10}$$

Note 1 to entry: The unit of **sound pressure gradient sensitivity level** is expressed as a level in decibels, dB.

Note 2 to entry: The reference value of sensitivity $M_{pg,ref}$ is 1 V·m·µPa^{-1}.

3.21
acoustic waveguide
apparatus for the guided transmission of sound within the confines of predetermined boundaries

4 List of symbols

a **sound particle acceleration**

a_0 acceleration of the projector surface

A acoustic pressure amplitude of wave travelling in the $+\hat{x}$ direction in a travelling wave tube

B acoustic pressure amplitude of wave travelling in the $-\hat{x}$ direction in a travelling wave tube