IEC TS 61934

Edition 3.0 2024-01
REDLINE VERSION

TECHNICAL SPECIFICATION

colour inside

Electrical insulating materials and systems – Electrical measurement of partial discharges (PD) under short rise time and repetitive voltage impulses



IEC TS 61934:2024-01 RLV(en)



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2024 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Secretariat
3, rue de Varembé
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC
The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications
The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform
The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, …). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished
Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc
If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC Products & Services Portal - products.iec.ch
Discover our powerful search engine and read freely all the publications previews, graphical symbols and the glossary. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org
The world's leading online dictionary on electrotechnology, containing more than 22 500 terminological entries in English and French, with equivalent terms in 25 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC TS 61934

Edition 3.0 2024-01
REDLINE VERSION

TECHNICAL SPECIFICATION

colour inside

Electrical insulating materials and systems – Electrical measurement of partial discharges (PD) under short rise time and repetitive voltage impulses

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 17.220.99; 29.035.01; 29.080.30

ISBN 978-2-8322-8189-5

Warning! Make sure that you obtained this publication from an authorized distributor.

® Registered trademark of the International Electrotechnical Commission

CONTENTS

FOREWORD 4
INTRODUCTION 2
1 Scope 7
2 Normative references 7
3 Terms and definitions 7
4 Measurement of partial discharge pulses during repetitive, short rise-time voltage impulses and comparison with power frequency 9
4.1 Measurement frequency 9
4.2 Measurement quantities 10
4.3 Test objects 10
4.3.1 General 10
4.3.2 Inductive test objects 10
4.3.3 Capacitive test objects 10
4.3.4 Distributed impedance test objects 10
4.4 Voltage impulse generators 11
4.4.1 General 11
4.4.2 Voltage impulse waveforms 11
4.5 Effect of testing conditions 12
4.5.1 General 12
4.5.2 Effect of environmental factors 12
4.5.3 Effect of testing conditions and ageing 12
5 PD detection methods 12
5.1 General 12
5.2 PD pulse coupling and detection devices 13
5.2.1 Introductory remarks 13
5.2.2 Coupling capacitor with multipole filter 13
5.2.3 HFCT with multipole filter 14
5.2.4 Electromagnetic couplers 15
5.2.5 Electromagnetic UHF antennae 15
~~5.2.5 Charge measurements~~ .....
~~5.3 Source-controlled gating techniques~~ .....
6 Measuring instruments 18
7 Sensitivity check of the PD measuring equipment and high voltage source generator 18
7.1 General 18
7.2 Test diagram for sensitivity check 18
7.3 PD detection sensitivity check 19
7.4 Background noise check 19
7.5 Detection system and HVIG noise check 19
7.6 Sensitivity report 20
8 Test procedure for increasing and decreasing the repetitive impulse voltage magnitude 20
9 Test report 22
Annex A (informative) Voltage impulse suppression required by the coupling device 24
Annex B (informative) PD pulses extracted from a supply voltage impulse through filtering techniques 26

Annex C (informative) Results of round-robin tests of RPDIV measurement 28
Annex D (informative) Examples of noise levels of practical PD detectors 30
Bibliography 31

Figure 1 – Coupling capacitor with multipole filter 13
Figure 2 – Example of voltage impulse and ideal PD pulse frequency spectra before and after filtering 14
Figure 3 – HFCT between supply and test object with multipole filter 15
Figure 4 – HFCT between test object and earth with multipole filter 15
Figure 5 – Circuit using an electromagnetic coupler (e.g. an antenna) to suppress impulses from the test supply 15
Figure 6 – Circuit using an electromagnetic UHF antenna 16
~~Figure 7 – Example of waveforms of repetitive bipolar impulse voltage and charge accumulation for a twisted-pair sample ..... ~~
~~Figure 8 – Charge measurements ..... ~~
~~Figure 9 – Example of PD detection using electronic source-controlled gating (other PD coupling devices can be used) ..... ~~
Figure 7 – Test diagram for sensitivity check 19
Figure 8 – Example of relation between the outputs of LVPG and PD detector 20
Figure 9 – Example of increasing and decreasing the impulse voltage magnitude 22
Figure A.1 – Example of overlap between voltage impulse and PD pulse spectra (dotted area) 24
Figure A.2 – Example of voltage impulse and PD pulse spectra after filtering 24
Figure A.3 – Example of impulse voltage damping as a function of impulse voltage magnitude and rise time 25
Figure B.1 – Power supply waveform and recorded signal using an antenna during supply voltage commutation 26
Figure B.2 – Signal detected by an antenna from the record of Figure B.1, using a filtering technique (400 MHz high-pass filter) 27
Figure B.3 – Characteristic of the filter used to pass from Figure B.1 to Figure B.2 27
Figure C.1 – Sequence of negative voltage impulses used for RRT 28
Figure C.2 – PD pulses corresponding to voltage impulses 29
Figure C.3 – Dependence of normalized RPDIV on 100 data (NRPDIV/100) on relative humidity 29

Table 1 – Example of parameter values of impulse voltage waveform without load 11
Table D.1 – Examples of bandwidths and noise levels for practical PD sensors 30

INTERNATIONAL ELECTROTECHNICAL COMMISSION

_____

ELECTRICAL INSULATING MATERIALS AND SYSTEMS – ELECTRICAL MEASUREMENT OF PARTIAL DISCHARGES (PD) UNDER SHORT RISE TIME AND REPETITIVE VOLTAGE IMPULSES

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This redline version of the official IEC Standard allows the user to identify the changes made to the previous edition IEC TS 61934:2011. A vertical bar appears in the margin wherever a change has been made. Additions are in green text, deletions are in strikethrough red text.

IEC TS 61934 has been prepared by IEC technical committee 112: Evaluation and qualification of electrical insulating materials and systems. It is a Technical Specification.

This third edition cancels and replaces the second edition published in 2011. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

a) background information on the progress being made in the field of power electronics including the introduction of wide band gap semiconductor devices has been added to the Introduction;

b) voltage impulse generators; the parameter values of the voltage impulse waveform have been modified to reflect application of wide band gap semiconductor devices.

c) PD detection methods; charge-based measurements are not described in this third edition nor are source-controlled gating techniques to suppress external noise.

d) Since the previous edition in 2011, there have been significant technical advances in this field as evidenced by several hundreds of publications. Consequently, the Bibliography in the 2011 edition has been deleted in this third edition.

The text of this Technical Specification is based on the following documents:

Draft	Report on voting
112/578/DTS	112/610/RVDTS

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this Technical Specification is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

Power electronics has been developed along with both control theory and semiconductor technology. Switching is one of the essential features of power electronics control. For higher efficiency and smoother operation, switching times of ~~the latest~~ devices such as an insulated-gate bipolar transistor (IGBT) tend to be shorter than microseconds. The introduction of wide band gap devices, such as those based on silicon carbide, can result in transients with rise times of the order of a few tens of nanoseconds. Such a short rise time ~~may~~ can cause transient overvoltage impulses or surges in systems. When the voltage impulses reach the breakdown strength of an air gap, partial discharge (PD) ~~may~~ can occur. In addition, the impulses are repetitive from power electronics modulation such as pulse width modulation (PWM). Since PD ~~may~~ can cause degradation of electrical insulation parts in the system, it is one of the most important parameters to be measured.

The first edition of IEC TS 61934 was issued in April 2006. Because of rapid development in this field, the revision activity for the latest information was approved by TC 112 at their Berlin meeting in September 2006. ~~In addition to technical and editorial changes, practical experience obtained through round-robin test (RRT) is also presented in Annex C.~~ The second edition of IEC TS 61934 was published in 2011. Owing to further advances in this area, a revision of the second edition was commenced formally in 2019 and has resulted in this third edition.

ELECTRICAL INSULATING MATERIALS AND SYSTEMS – ELECTRICAL MEASUREMENT OF PARTIAL DISCHARGES (PD) UNDER SHORT RISE TIME AND REPETITIVE VOLTAGE IMPULSES

1 Scope

This document is applicable to the off-line electrical measurement of partial discharges (PDs) that occur in electrical insulation systems (EISs) when stressed by repetitive voltage impulses generated from ~~electronic~~ power electronics devices.

Typical applications are EISs belonging to apparatus driven by power electronics, such as motors, inductive reactors ~~and windmill~~, wind turbine generators and the power electronics modules themselves.

NOTE ~~1~~ Use of this document with specific products ~~may~~ can require the application of additional procedures.

~~NOTE 2 The procedures described in this technical specification are emerging technologies. Experience and caution, as well as certain preconditions, are needed to apply it.~~

Excluded from the scope of this document are

– methods based on optical or ultrasonic PD detection,
– fields of application for PD measurements when stressed by non-repetitive impulse voltages such as lightning impulse or switching impulses from switchgear.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

~~IEC 60034 (all parts), *Rotating electrical machines*~~

IEC 60270~~:2000~~, *High-voltage test techniques – Partial discharge measurements*

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminology databases for use in standardization at the following addresses:

- IEC Electropedia: available at https://www.electropedia.org/
- ISO Online browsing platform: available at https://www.iso.org/obp

3.1
repetitive voltage impulse
voltage impulse which is used as test voltage for the evaluation of switching surges from power electronics devices with a carrier or driven frequency

3.2
partial discharge
PD
localized electric discharge that only partially bridges the insulation between conductors and which can or cannot occur adjacent to a conductor

~~[IEC 60270:2000, 3.1, modified]~~

3.3
partial discharge pulse
current pulse in an object under test that results from a partial discharge occurring within the object under test

Note 1 to entry: The pulse is measured using suitable detector circuits, which have been introduced into the test circuit for the purpose of the test.

Note 2 to entry: A detector in accordance with the provisions of this document produces a current or a voltage signal at its output related to the PD pulse at its input.

[SOURCE: IEC 60270~~:2000~~, 3.2, modified – "or voltage" has been deleted, the second part of the definition has been included in Note 1 to entry and Note 2 to entry has been revised.]

3.4
RPDIV
repetitive partial discharge inception voltage
minimum peak-to-peak impulse voltage at which more than five PD pulses occur on ten voltage impulses of the same polarity

Note 1 to entry: The RPDIV is a mean value for the specified test time and a test arrangement where the voltage applied to the test object is gradually increased from a value at which no partial discharges can be detected. Further explanation is mentioned in 8.

3.5
RPDEV
repetitive partial discharge extinction voltage
maximum peak-to-peak impulse voltage at which less than five PD pulses occur on ten voltage impulses of the same polarity

Note 1 to entry: The RPDEV is a mean value for a specified test time and a test arrangement where the voltage applied to the test object gradually decreases from a voltage at which PDs have been detected. Further explanation is mentioned in Clause 8.

3.6
impulse voltage polarity
polarity of the applied impulse voltage with respect to earth

~~[IEC 62068-1:2003, 3.10]~~

3.7
unipolar impulse
repetitive voltage impulse, the polarity of which is either positive or negative

~~[IEC 62068-1:2003, 3.8, modified]~~

~~NOTE The magnitude of the oscillation of the opposite polarity has to be less than 20 %.~~

[SOURCE: IEC 62068:2013, 3.11, modified – "repetitive" has been added.]

3.8
bipolar impulse
repetitive voltage impulse, the polarity of which changes from positive to negative or vice versa

~~[IEC 62068-1:2003, 3.9, modified]~~

3.9
impulse voltage repetition rate
inverse of the average time between successive impulses of the same polarity, whether unipolar or bipolar

~~[IEC 62068-1:2003, 3.11, modified]~~

3.10
impulse rise time
time for the voltage ~~impulse to go~~ to rise from ~~0 % to 100 %~~ 10 % to 90 %

~~NOTE Unless otherwise stated, this is estimated as 1,25 times the time for the voltage to rise from 10 % to 90 %.~~

3.11
impulse decay time
time interval between the instants at which the instantaneous value of an impulse decreases from a specified upper value to a specified lower value

Note 1 to entry: Unless otherwise specified, the upper and lower values are fixed at 90 % and 10 % of the impulse magnitude.

3.12
impulse width
interval of time between the first and last instants at which the instantaneous value of an impulse reaches a specified fraction of impulse magnitude or a specified threshold

3.13
impulse duty cycle
ratio, for a given time interval, of the impulse width to the total time

3.14
peak partial discharge magnitude
largest magnitude of any quantity related to PD pulses observed in a test object at a specified voltage following a specified conditioning and test

Note 1 to entry: For impulse voltage tests, the peak magnitude of the PD pulse is the largest repeatedly occurring PD magnitude.

[SOURCE: IEC 60270~~:2000~~, 3.4, modified – In the term “largest repeatedly occurring” has been replaced with “peak”, the definition has been revised and the Note to entry has been added.]

4 Measurement of partial discharge pulses during repetitive, short rise-time voltage impulses and comparison with power frequency

4.1 Measurement frequency

IEC 60270 describes the methods employed to measure the electrical pulses associated with PD in test objects excited by DC and alternating voltages up to 400 Hz. The methods used to measure PD pulses when the test object is subjected to supply voltage impulses ~~have to~~ shall be modified from the standard narrow-band and wide-band frequency methods described in IEC 60270.

To measure the PD during repetitive short rise time voltage impulses, it is necessary to avoid the induced current of the ~~excited~~ impulse voltage. One technique is current or electromagnetic wave measurement at ultra-high frequency, that is, higher than ~~that of~~ the frequency components associated with the impulse. Ultra-wide band (UWB) detection is often used with a high-pass filter for the suppression of the relatively lower frequency components of the impulse voltage. In principle, narrow-band measurement in the ultra-high frequency (UHF: 300 MHz to 3 GHz) region is also effective for the suppression of the impulse voltage. ~~The other method is~~

~~the integration of PD current at a very low frequency compared to that of the impulse voltage.~~ Partial discharge measurement methods in this frequency range are described in IEC TS 62478.

NOTE Measurements in accordance with IEC TS 62478 cannot be calibrated in relation to apparent charge in pC, so a direct value-based comparison to measurements in accordance with IEC 60270 is not possible.

4.2 Measurement quantities

Measured quantities concern the RPDIV, the RPDEV, the peak partial discharge magnitude and partial discharge pulse repetition rate.

The RPDIV and RPDEV ~~may~~ can depend on PD measurement sensitivity and measurement circuit noise, therefore normalization, as indicated in Clause 7, is ~~needed~~ necessary. Moreover, they depend on the test object and the pulse deformation from the discharge site to the measurement point.

In this document, and consistent with IEC TS 62478, PD readings are reported in units of mV. In all cases, a sensitivity evaluation of the measuring system is necessary and shall be carried out according to Clause 7.

4.3 Test objects

4.3.1 General

Test objects behave predominantly as inductive, capacitive or distributed equivalent impedances according to the voltage supply frequency content. For some test objects, whether they are predominantly inductive, capacitive or distributed, impedances ~~may~~ can depend on the PD detection frequency range (not only on the voltage supply frequency). Test objects with distributed behaviour have transmission line characteristics which ~~may~~ can cause attenuation and distortion of the PD pulses as the pulses propagate through the test object. The following classification is effective only for low-frequency, narrow-band measurements.

4.3.2 Inductive test objects

Types of inductive test objects ~~may~~ can include:

– stator and rotor windings
– inductive reactors
– transformer windings
– motorettes and formettes: see ~~the IEC 60034 series~~ IEC 60034-18-1

4.3.3 Capacitive test objects

Types of capacitive test objects ~~may~~ can include:

– twisted pairs of winding wire
– capacitors
– packaging of switching devices
– power electronics modules and substrates
– isolated heat sinks
– main wall insulation models in stator coils and bars
– printed circuit boards
– optocouplers

4.3.4 Distributed impedance test objects

The following test objects ~~may~~ can have distributed equivalent impedance properties: