INTERNATIONAL STANDARD

ISO 16610-28

First edition
2016-12-15

Geometrical product specifications (GPS) — Filtration —

Part 28: Profile filters: End effects

Spécification géométrique des produits (GPS) — Filtrage —

Partie 28: Filtres de profil: Effets de bords

Reference number
ISO 16610-28:2016(E)

© ISO 2016



COPYRIGHT PROTECTED DOCUMENT

© ISO 2016, Published in Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Ch. de Blandonnet 8 • CP 401
CH-1214 Vernier, Geneva, Switzerland
Tel. +41 22 749 01 11
Fax +41 22 749 09 47
copyright@iso.org
www.iso.org

 © ISO 2016 – All rights reserved

Contents

Page

Foreword ... **iv**
Introduction ... **v**
1 Scope ... **1**
2 Normative references ... **1**
3 Terms and definitions ... **1**
4 End effect correction methods ... **2**
4.1 General ... 2
4.2 Extrapolation of the profile — Methods ... 4
4.2.1 Zero padding ... 4
4.2.2 Linear extrapolation ... 5
4.2.3 Symmetric extension ... 6
4.3 Moment retainment criterion ... 8
5 Recommendations ... **14**
5.1 Default end correction ... 14
5.2 End correction designations ... 15
Annex A (normative) **Filters according to ISO 16610 with automatic correction of end effects** ... **16**
Annex B (informative) **Relationship to the filtration matrix model** ... **18**
Annex C (informative) **Relationship to the GPS matrix model** ... **19**
Bibliography ... **20**

© ISO 2016 – All rights reserved

Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular the different approval criteria needed for the different types of ISO documents should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see www.iso.org/directives).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation on the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT) see the following URL: www.iso.org/iso/foreword.html.

This document was prepared by Technical Committee ISO/TC 213, *Dimensional and geometrical product specifications and verification*.

This first edition of ISO 16610-28 cancels and replaces ISO/TS 16610-28:2010, which has been technically revised.

A list of all parts in the ISO 16610 series can be found on the ISO website.

© ISO 2016 – All rights reserved

Introduction

This document is a geometrical product specification (GPS) standard and is to be regarded as a general GPS standard (see ISO 14638). It influences the chain link C of all chains of standards.

The ISO/GPS Matrix model given in ISO 14638 gives an overview of the ISO/GPS system of which this document is a part. The fundamental rules of ISO/GPS given in ISO 8015 apply to this document and the default decision rules given in ISO 14253-1 apply to specifications made in accordance with this document, unless otherwise indicated.

For more detailed information of the relation of this document to the GPS matrix model, see Annex C.

This document develops the concept of handling end effects in the case of linear profile filters.

© ISO 2016 – All rights reserved

Geometrical product specifications (GPS) — Filtration —

Part 28:
Profile filters: End effects

1 Scope

This document provides methods for treating the end effects of linear profile filters where such effects occur.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO 16610-1, *Geometrical product specifications (GPS) — Filtration — Part 1: Overview and basic concepts*

ISO 16610-20, *Geometrical product specifications (GPS) — Filtration — Part 20: Linear profile filters: Basic concepts*

ISO 16610-21, *Geometrical product specifications (GPS) — Filtration — Part 21: Linear profile filters: Gaussian filters*

ISO 16610-22, *Geometrical product specifications (GPS) — Filtration — Part 22: Linear profile filters: Spline filters*

ISO 16610-31, *Geometrical product specifications (GPS) — Filtration — Part 31: Robust profile filters: Gaussian regression filters*

ISO/TS 16610-32, *Geometrical product specifications (GPS) — Filtration — Part 32: Robust profile filters: Spline filters*

ISO/IEC Guide 99, *International vocabulary of metrology — Basic and general concepts and associated terms (VIM)*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in ISO/IEC Guide 99, ISO 16610-1, ISO 16610-20, ISO 16610-21, ISO 16610-22, ISO 16610-31, ISO/TS 16610-32 and the following apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

— IEC Electropedia: available at http://www.electropedia.org/

— ISO Online browsing platform: available at http://www.iso.org/obp

3.1
end effect
unintentional changes in the filtration response in the end portions of an open profile

3.2
end effect region
end portion of an open profile where end effects are significant

© ISO 2016 – All rights reserved

3.3
moment
*n*th moment, μ_n, of a real valued function $f(x)$, defined by

$$\mu_n = \int_{-\infty}^{\infty} x^n \times f\left(x\right) \times \mathrm{d}x$$

3.4
moment criterion
criterion applying to the shift invariant filter class of a linear profile filter where the weighting function of the filtration operation has vanishing moments up to the *n*th order, as expressed by

$$\int_{\Omega} x^p \times s\left(x\right) \times \mathrm{d}x = 0, \quad p = 1\,, \ldots, n$$

where

$s(x)$ is the weighting function of the filter and Ω the definition area of the weighting function

4 End effect correction methods

4.1 General

A linear shift invariant profile filter can be implemented as a weighted moving average with a constant weighting function, $s(x)$, e.g. the Gaussian bell curve according to ISO 16610-21. Because the measured profile, $z(x)$, is always finite, $s(x)$ shall have a local support, $-l_1 \le x \le l_2$, which is normally much smaller than the traversing length. Therefore, the filter formula for the low-pass filter based on the convolution is defined as

$$w\left(x\right) = \int_{-l_1}^{l_2} z\left(x-u\right) \times s\left(u\right) \times \mathrm{d}u = \int_{x-l_2}^{x+l_1} z\left(u\right) \times s\left(x-u\right) \times \mathrm{d}u, \quad l_2 \le x \le l_t - l_1 \tag{1}$$

where

$w(x)$ is the reference line;

$z(x)$ is the measured profile;

l_t is the measuring length.

In contrast to profile $z(x)$, reference line $w(x)$ is only valid for $l_2 \le x \le l_t - l_1$. The end effect regions are $B_2 = [0, l_2]$ and $B_1 = [l_t - l_1, l_t]$.

NOTE 1 For simplicity, only continuous weighting functions $s(x)$ are considered in this document. The methods are also valid for discrete weighting functions.

NOTE 2 The procedure can be applied directly to the profile or can modify the filtration operation.

EXAMPLE In the case of the standardized Gaussian filter (see ISO 16610-21), the weighting function has a local support, e.g. $l_1 = l_2 = \lambda_c/2$. As shown in Figure 1, the filter formula cannot be applied over the whole traversing length. In the end effect region, either the left side or the right side of the Gaussian bell curve lies outside the profile.

© ISO 2016 – All rights reserved