AS 60034.26-2009
IEC 60034-26:2006
Reconfirmed 2021
IEC 60034-26:2006/COR1:2014
(Incorporating Amendment No. 1)

Australian STANDARD®

STANDARDS Australia

Rotating electrical machines

Part 26: Effects of unbalanced voltages on the performance of three-phase induction motors



AS 60034.26-2009

This Australian Standard ® was prepared by Committee EL-009, Rotating Electrical Machinery. It was approved on behalf of the Council of Standards Australia on 11 June 2009.

This Standard was published on 15 July 2009.

The following are represented on Committee EL-009:

Airconditioning and Refrigeration Equipment Manufacturers Association of Australia
Australian Chamber of Commerce and Industry
Australian Electrical and Electronic Manufacturers Association
Australian Greenhouse Office, Department of the Environment and Water Resources
Australian Industry Group
Bureau of Steel Manufacturers of Australia
Department of Defence (Australia)
Electrical Apparatus Service Association
Energy Efficiency and Conservation Authority of New Zealand
Engineers Australia
Ministry of Economic Development (New Zealand)
Registered Master Builders

This Standard was issued in draft form for comment as DR 08201.

Keeping Standards up-to-date

Ensure you have the latest versions of our publications and keep up-to-date about Amendments, Rulings, Withdrawals, and new projects by visiting:
www.standards.org.au

ISBN 0 7337 9195 6

STANDARDS AUSTRALIA

RECONFIRMATION

OF
AS 60034.26—2009
Rotating electrical machines
Part 26: Effects of unbalanced voltages on the performance of three-phase induction motors

RECONFIRMATION NOTICE

Technical Committee EL-009 has reviewed the content of this publication and in accordance with Standards Australia procedures for reconfirmation, it has been determined that the publication is still valid and does not require change.

Certain documents referenced in the publication may have been amended since the original date of publication. Users are advised to ensure that they are using the latest versions of such documents as appropriate, unless advised otherwise in this Reconfirmation Notice.

Approved for reconfirmation in accordance with Standards Australia procedures for reconfirmation on 14 July 2021.

The following are represented on Technical Committee EL-009:

Fan Manufacturers Association of Australia and New Zealand
Airconditioning & Refrigeration Equipment Manufacturers Association of Australia
Department of Industry, Science, Energy and Resources
Australian Industry Group
Engineers Australia
Registered Master Builders

AS 60034.26-2009
IEC 60034-26:2006
IEC 60034-26:2006/COR1:2014
(Incorporating Amendment No. 1)

Rotating electrical machines

Part 26: Effects of unbalanced voltages on the performance of three-phase induction motors

First published as AS 60034.26 2009.
Reissued incorporating Amendment No 1 (November 2023).

© IEC Geneva Switzerland 2023
© Standards Australia Limited 2023

All rights are reserved. No part of this work may be reproduced or copied in any form or by any means, electronic or mechanical, including photocopying, without the written permission of the publisher, unless otherwise permitted under the Copyright Act 1968 (Cth).

Preface

This Standard was prepared by the Joint Standards Australia/Standards New Zealand Committee EL-009, Rotating Electrical Machinery.

This Standard was prepared by the Australian members of the Joint Standards Australia/Standards New Zealand Committee EL-009. After consultation with stakeholders in both countries, Standards Australia and Standards New Zealand decided to develop this Standard as an Australian Standard rather than an Australian/New Zealand Standard.

〈A1〉 Amendment No. 1 to this Standard was prepared by the Joint Standards Australia/Standards New Zealand Committee EL-009, Rotating Electrical Machinery. 〈A1〉

〈A1〉 *This Standard incorporates Amendment No. 1 (November 2023). The start and end of changes introduced by the Amendment are indicated in the text by tags including the Amendment number 1.* 〈A1〉

The objective of this Standard is to highlight the effects of unbalanced voltages on the performance of cage induction motors.

〈A1〉 This Standard is identical with, and has been reproduced from IEC 60034-26, Ed. 1 (2006), *Rotating electrical machines – Part 26: Effects of unbalanced voltages on the performance of three-phase cage induction motors* and its Corrigendum 1 (2014), which has been added at the end of the source text. 〈A1〉

This Standard is Part 26 of a Series dealing with rotating electrical machinery. Additional parts will be added from time to time. This Series when complete will consist of the following parts:

AS 1359.102.2, *Rotating electrical machines—Methods for determining losses and efficiency of rotating electrical machinery from tests—Measurement of losses by the calorimetric method*

AS 60034.1, *Rotating electrical machines, Part 1: Rating and performance*

AS 60034.2.1, *Rotating electrical machines, Part 2.1: Methods for determining losses and efficiency from tests (excluding machines for traction vehicles)*

AS 60034.3, *Rotating electrical machines, Part 3: Specific requirements for synchronous generators driven by steam turbines or combustion gas turbines*

AS 60034.4, *Rotating electrical machines, Part 4: Methods for determining synchronous machine quantities from tests*

AS 60034.5, *Rotating electrical machines, Part 5: Degrees of protection provided by the integral design of rotating electrical machines (IP code)—Classification*

AS 60034.6, *Rotating electrical machines, Part 6: Method of cooling (IC code)*

AS 60034.7, *Rotating electrical machines, Part 7: Classification of types of construction, mounting arrangements and terminal box position (IM code)*

AS 60034.8, *Rotating electrical machines, Part 8: Terminal markings and direction of rotation*

AS 60034.9, *Rotating electrical machines, Part 9: Noise limits*

AS 60034.11, *Rotating electrical machines, Part 11: Thermal protection*

AS 60034.12, *Rotating electrical machines, Part 12: Starting performance of single-speed three-phase cage induction motors*

AS 60034.14, *Rotating electrical machines, Part 14: Mechanical vibration of certain machines with shaft heights 56 mm and higher—Measurement, evaluation and limits of vibration severity*

AS 60034.15, *Rotating electrical machines, Part 15: Impulse voltage withstand levels of rotating a.c. machines with form-wound stator coils*

© Standards Australia Limited 2023

AS 60034.16, *Rotating electrical machines, Part 16: Excitation systems for synchronous machines (all parts)*

AS 60034.17, *Rotating electrical machines, Part 17: Cage induction motors when fed from converters—Application guide*

AS 60034.18, *Rotating electrical machines, Part 18: Functional evaluation of insulation systems (all parts)*

AS 60034.19, *Rotating electrical machines, Part 19: Specific test methods for d.c. machines on conventional and rectifier-fed supplies*

AS 60034.20.1, *Rotating electrical machines, Part 20.1: Control motors—Stepping motors*

AS 60034.22, *Rotating electrical machines, Part 22: AC generators for reciprocating internal combustion (RIC) engine driven generating sets*

AS 60034.23, *Rotating electrical machines, Part 23: Specification for the refurbishing of rotating electrical machines*

AS 60034.25, *Rotating electrical machines, Part 25: Guidance for the design and performance of a.c. motors specifically designed for converter supply*

AS 60034.26, *Rotating electrical machines, Part 26: Effects of unbalanced voltages on the performance of three-phase cage induction motors(this Standard)*

AS 60034.27, *Rotating electrical machines, Part 27: Off-line partial discharge measurements on the stator winding insulation of rotating electrical machines*

AS 60034.28, *Rotating electrical machines, Part 28: Test methods for determining quantities of equivalent circuit diagrams for the three-phase low voltage cage induction motors*

AS 60034.29, *Rotating electrical machines, Part 29: Equivalent loading and superposition techniques—Indirect testing to determine temperature rise*

As this Standard is reproduced from an International Standard, the following applies:

(a) Its number does not appear on each page of text and its identity is shown only on the cover and title page.

(b) In the source text 'IEC 60034-26' should read 'AS 60034.26'.

(c) A full point should be substituted for a comma when referring to a decimal marker.

The terms 'normative' and 'informative' are used to define the application of the annex to which they apply. A normative annex is an integral part of a standard, whereas an informative annex is only for information and guidance.

© Standards Australia Limited 2023

NOTES

CONTENTS

FOREWORD 5
INTRODUCTION 9

1 Scope 11
2 Normative references 11
3 Effects of unbalanced voltages on performance 11
3.1 Currents 11
3.2 Heating 11
3.3 Torques 13
3.4 Full-load speed 13
4 Derating of motor to prevent overheating 13

Annex A (informative) Determination of the symmetrical components of the line-to-line voltages U_1, U_2, U_3 of a three-phase system 17
Annex B (informative) Approximate determination 21

Figure 1 – Typical values of derating of design N, three-phase cage induction motors within the scope of IEC 60034-12 15
Figure A.1 – Phasor diagram 17

© Standards Australia Limited 2023

INTERNATIONAL ELECTROTECHNICAL COMMISSION

ROTATING ELECTRICAL MACHINES –

Part 26: Effects of unbalanced voltages on the performance of three-phase cage induction motors

FOREWORD

1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
6) All users should ensure that they have the latest edition of this publication.
7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60034-26 has been prepared by IEC technical committee 2: Rotating machinery.

This standard cancels and replaces IEC TS 60034-26 published in 2002.

The text of this standard is based on the following documents:

FDIS	Report on voting
2/1391/FDIS	2/1398/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

© Standards Australia Limited 2023

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts of IEC 60034 series, under the general title *Rotating electrical machines* can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

The contents of the corrigendum of September 2014 have been included in this copy.

© Standards Australia Limited 2023

INTRODUCTION

When the line voltages applied to a three-phase cage induction motor are not equal, the currents in the stator windings will also be unequal. A small percentage voltage unbalance will result in a much larger percentage current unbalance.

The application of unbalanced voltages to a three-phase induction motor introduces a negative sequence voltage, and this produces in the air gap, a flux rotating against the rotation of the rotor, thus tending to produce high currents. A small negative sequence voltage may produce currents in the windings considerably in excess of those present under balanced voltage conditions. Consequently, the temperature rise of the motor operating at a particular load and percentage of voltage unbalance will be greater than for the motor operating under the same conditions with balanced voltages.

The analytical and graphical methods used to calculate the symmetrical components from the voltage readings of the three phases are well-known and can be taken from textbooks. Thus, the calculation schemes are not incorporated in this standard, but shown in the informative Annex A. Besides, the evaluation of the symmetrical components can be done automatically by modern instrumentation.

An approximate evaluation of imbalance is given in the informative Annex B.

© Standards Australia Limited 2023

ROTATING ELECTRICAL MACHINES –

Part 26: Effects of unbalanced voltages on the performance of three-phase cage induction motors

1 Scope

This part of IEC 60034 describes the effects of unbalanced voltages on the performance of three-phase cage induction motors.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60034-12, *Rotating electrical machines – Part 12: Starting performance of single-speed three-phase cage induction motors*

3 Effects of unbalanced voltages on performance

The effects of unbalanced voltages on motor performance are as described in 3.1 to 3.3.

3.1 Currents

The negative sequence components of the voltage produce in the air gap a flux rotating against the rotation of the rotor. A small negative-sequence component of the voltage may produce currents in the windings considerably in excess of those present under balanced voltage conditions. The frequency of the current in the cage is almost twice rated frequency, thus in the case of cages with current displacement the increase of the rotor winding losses is substantially higher than the increase of the stator winding losses.

The currents at normal operating speed will be greatly unbalanced in the order of approximately 6 to 10 times the voltage unbalance.

The locked-rotor current will be unbalanced to the same degree that the voltages are unbalanced, but the locked-rotor apparent power will increase only slightly.

3.2 Heating

The temperature rise of the stator winding is always higher than in operation at balanced supply voltages due to the increase of the losses produced by the negative-sequence components of the currents and voltages.

The increase of the rotor losses is amplified by the current displacement.

© Standards Australia Limited 2023